




## 3.5"-SBC-WLU

Doc. User Guide, Rev. 2.2

Doc. ID: [To be Determined]

This page has been intentionally left blank

 3.5"-SBC-WLU - USER GUIDE

## Disclaimer

Kontron would like to point out that the information contained in this user guide may be subject to alteration, particularly as a result of the constant upgrading of Kontron products. This document does not entail any guarantee on the part of Kontron with respect to technical processes described in the user guide or any product characteristics set out in the user guide. Kontron assumes no responsibility or liability for the use of the described product(s), conveys no license or title under any patent, copyright or mask work rights to these products and makes no representations or warranties that these products are free from patent, copyright or mask work right infringement unless otherwise specified. Applications that are described in this user guide are for illustration purposes only. Kontron makes no representation or warranty that such application will be suitable for the specified use without further testing or modification. Kontron expressly informs the user that this user guide only contains a general description of processes and instructions which may not be applicable in every individual case. In cases of doubt, please contact Kontron.

This user guide is protected by copyright. All rights are reserved by Kontron. No part of this document may be reproduced, transmitted, transcribed, stored in a retrieval system, or translated into any language or computer language, in any form or by any means (electronic, mechanical, photocopying, recording, or otherwise), without the express written permission of Kontron. Kontron points out that the information contained in this user guide is constantly being updated in line with the technical alterations and improvements made by Kontron to the products and thus this user guide only reflects the technical status of the products by Kontron at the time of publishing.

Brand and product names are trademarks or registered trademarks of their respective owners.

©2025 by Kontron Europe GmbH

Kontron Europe GmbH

Gutenbergstraße 2  
85737 Ismaning  
Germany  
[www.kontron.com](http://www.kontron.com)

## Intended Use

**THIS DEVICE AND ASSOCIATED SOFTWARE ARE NOT DESIGNED, MANUFACTURED OR INTENDED FOR USE OR RESALE FOR THE OPERATION OF NUCLEAR FACILITIES, THE NAVIGATION, CONTROL OR COMMUNICATION SYSTEMS FOR AIRCRAFT OR OTHER TRANSPORTATION, AIR TRAFFIC CONTROL, LIFE SUPPORT OR LIFE SUSTAINING APPLICATIONS, WEAPONS SYSTEMS, OR ANY OTHER APPLICATION IN A HAZARDOUS ENVIRONMENT, OR REQUIRING FAIL-SAFE PERFORMANCE, OR IN WHICH THE FAILURE OF PRODUCTS COULD LEAD DIRECTLY TO DEATH, PERSONAL INJURY, OR SEVERE PHYSICAL OR ENVIRONMENTAL DAMAGE (COLLECTIVELY, "HIGH RISK APPLICATIONS").**

You understand and agree that your use of Kontron devices as a component in High Risk Applications is entirely at your risk. To minimize the risks associated with your products and applications, you should provide adequate design and operating safeguards. You are solely responsible for compliance with all legal, regulatory, safety, and security related requirements concerning your products. You are responsible to ensure that your systems (and any Kontron hardware or software components incorporated in your systems) meet all applicable requirements. Unless otherwise stated in the product documentation, the Kontron device is not provided with error-tolerance capabilities and cannot therefore be deemed as being engineered, manufactured or setup to be compliant for implementation or for resale as device in High Risk Applications. All application and safety related information in this document (including application descriptions, suggested safety measures, suggested Kontron products, and other materials) is provided for reference only.

## Revision History

| Revision | Brief Description of Changes                   | Date of Issue | Author/<br>Editor |
|----------|------------------------------------------------|---------------|-------------------|
| 1.0      | Initial Issue                                  | 2020-Feb-26   | YS                |
| 1.1      | Add a LPS power supply notice in Sec. 2.1      | 2020-Mar-31   | YS                |
| 1.2      | Add mating connector info                      | 2020-Oct-26   | YS                |
| 1.3      | Add extended temperature                       | 2020-Oct-28   | YS                |
| 1.4      | Remove extended temperature                    | 2021-Apr-15   | YS                |
| 1.5      | Modify USB 3.1 to USB 3.2 Gen 2 per new naming | 2021-Sep-08   | YS                |
| 1.6      | Add max. current value                         | 2021-Dec-06   | YS                |
| 1.7      | Modify audio codec                             | 2022-Jan-12   | YS                |
| 1.8      | Add extended temperature                       | 2023-Jan-30   | YS                |
| 2.0      | Update power consumption                       | 2024-Apr-03   | YS                |
| 2.1      | Remove extended temperature                    | 2024-Sep-02   | YS                |
| 2.2      | Revise power consumption table                 | 2025-Aug-15   | YS                |

## Terms and Conditions

Kontron warrants products in accordance with defined regional warranty periods. For more information about warranty compliance and conformity, and the warranty period in your region, visit <https://www.kontron.com/terms-and-conditions>.

Kontron sells products worldwide and declares regional General Terms & Conditions of Sale, and Purchase Order Terms & Conditions. Visit <https://www.kontron.com/terms-and-conditions>.

For contact information, refer to the corporate offices contact information on the last page of this user guide or visit our website [CONTACT US](#).

## Customer Support

Find Kontron contacts by visiting: <https://www.kontron.com/support>.

## Customer Service

As a trusted technology innovator and global solutions provider, Kontron extends its embedded market strengths into a services portfolio allowing companies to break the barriers of traditional product lifecycles. Proven product expertise coupled with collaborative and highly-experienced support enables Kontron to provide exceptional peace of mind to build and maintain successful products.

For more details on Kontron's service offerings such as: enhanced repair services, extended warranty, Kontron training academy, and more visit <https://www.kontron.com/support-and-services/services>.

## Customer Comments

If you have any difficulties using this user guide, discover an error, or just want to provide some feedback, contact [Kontron support](#). Detail any errors you find. We will correct the errors or problems as soon as possible and post the revised user guide on our website.

## Symbols

The following symbols may be used in this user guide

### **⚠ DANGER**

DANGER indicates a hazardous situation which, if not avoided, will result in death or serious injury.

### **⚠ WARNING**

WARNING indicates a hazardous situation which, if not avoided, could result in death or serious injury.

### **NOTICE**

NOTICE indicates a property damage message.

### **⚠ CAUTION**

CAUTION indicates a hazardous situation which, if not avoided, may result in minor or moderate injury.



#### Electric Shock!

This symbol and title warn of hazards due to electrical shocks (> 60 V) when touching products or parts of products. Failure to observe the precautions indicated and/or prescribed by the law may endanger your life/health and/or result in damage to your material.



#### ESD Sensitive Device!

This symbol and title inform that the electronic boards and their components are sensitive to static electricity. Care must therefore be taken during all handling operations and inspections of this product in order to ensure product integrity at all times.



#### HOT Surface!

Do NOT touch! Allow to cool before servicing.



#### Laser!

This symbol inform of the risk of exposure to laser beam and light emitting devices (LEDs) from an electrical device. Eye protection per manufacturer notice shall review before servicing.



This symbol indicates general information about the product and the user guide.

This symbol also indicates detail information about the specific product configuration.



This symbol precedes helpful hints and tips for daily use.

## For Your Safety

Your new Kontron product was developed and tested carefully to provide all features necessary to ensure its compliance with electrical safety requirements. It was also designed for a long fault-free life. However, the life expectancy of your product can be drastically reduced by improper treatment during unpacking and installation. Therefore, in the interest of your own safety and of the correct operation of your new Kontron product, you are requested to conform with the following guidelines.

### High Voltage Safety Instructions

As a precaution and in case of danger, the power connector must be easily accessible. The power connector is the product's main disconnect device.

#### **⚠ CAUTION**

##### Warning

All operations on this product must be carried out by sufficiently skilled personnel only.

#### **⚠ CAUTION**



##### Electric Shock!

Before installing a non hot-swappable Kontron product into a system always ensure that your mains power is switched off. This also applies to the installation of piggybacks. Serious electrical shock hazards can exist during all installation, repair, and maintenance operations on this product. Therefore, always unplug the power cable and any other cables which provide external voltages before performing any work on this product.

Earth ground connection to vehicle's chassis or a central grounding point shall remain connected. The earth ground cable shall be the last cable to be disconnected or the first cable to be connected when performing installation or removal procedures on this product.

### Special Handling and Unpacking Instruction

#### **NOTICE**



##### ESD Sensitive Device!

Electronic boards and their components are sensitive to static electricity. Therefore, care must be taken during all handling operations and inspections of this product, in order to ensure product integrity at all times.

Do not handle this product out of its protective enclosure while it is not used for operational purposes unless it is otherwise protected.

Whenever possible, unpack or pack this product only at EOS/ESD safe work stations. Where a safe work station is not guaranteed, it is important for the user to be electrically discharged before touching the product with his/her hands or tools. This is most easily done by touching a metal part of your system housing.

It is particularly important to observe standard anti-static precautions when changing piggybacks, ROM devices, jumper settings etc. If the product contains batteries for RTC or memory backup, ensure that the product is not placed on conductive surfaces, including anti-static plastics or sponges. They can cause short circuits and damage the batteries or conductive circuits on the product.

## Lithium Battery Precautions

If your product is equipped with a lithium battery, take the following precautions when replacing the battery.

### ⚠ CAUTION

**Danger of explosion if the battery is replaced incorrectly.**

- ▶ Replace only with same or equivalent battery type recommended by the manufacturer.
- ▶ Dispose of used batteries according to the manufacturer's instructions.

## General Instructions on Usage

In order to maintain Kontron's product warranty, this product must not be altered or modified in any way. Changes or modifications to the product, that are not explicitly approved by Kontron and described in this user guide or received from Kontron Support as a special handling instruction, will void your warranty.

This product should only be installed in or connected to systems that fulfill all necessary technical and specific environmental requirements. This also applies to the operational temperature range of the specific board version that must not be exceeded. If batteries are present, their temperature restrictions must be taken into account.

In performing all necessary installation and application operations, only follow the instructions supplied by the present user guide.

Keep all the original packaging material for future storage or warranty shipments. If it is necessary to store or ship the product then re-pack it in the same manner as it was delivered.

Special care is necessary when handling or unpacking the product. See Special Handling and Unpacking Instruction.

## Quality and Environmental Management

Kontron aims to deliver reliable high-end products designed and built for quality, and aims to complying with environmental laws, regulations, and other environmentally oriented requirements. For more information regarding Kontron's quality and environmental responsibilities, visit <https://www.kontron.com/about-kontron/corporate-responsibility/quality-management>.

## Disposal and Recycling

Kontron's products are manufactured to satisfy environmental protection requirements where possible. Many of the components used are capable of being recycled. Final disposal of this product after its service life must be accomplished in accordance with applicable country, state, or local laws or regulations.

## WEEE Compliance

The Waste Electrical and Electronic Equipment (WEEE) Directive aims to:

- ▶ Reduce waste arising from electrical and electronic equipment (EEE)
- ▶ Make producers of EEE responsible for the environmental impact of their products, especially when the product become waste
- ▶ Encourage separate collection and subsequent treatment, reuse, recovery, recycling and sound environmental disposal of EEE
- ▶ Improve the environmental performance of all those involved during the lifecycle of EEE



**Environmental protection is a high priority with Kontron.**

**Kontron follows the WEEE directive**

**You are encouraged to return our products for proper disposal.**

# Table of Contents

|                                                       |           |
|-------------------------------------------------------|-----------|
| <b>Symbols .....</b>                                  | <b>6</b>  |
| <b>For Your Safety .....</b>                          | <b>7</b>  |
| High Voltage Safety Instructions .....                | 7         |
| Special Handling and Unpacking Instruction .....      | 7         |
| Lithium Battery Precautions .....                     | 8         |
| <b>General Instructions on Usage .....</b>            | <b>8</b>  |
| <b>Quality and Environmental Management .....</b>     | <b>8</b>  |
| Disposal and Recycling .....                          | 8         |
| WEEE Compliance .....                                 | 8         |
| <b>Table of Contents .....</b>                        | <b>9</b>  |
| <b>List of Tables .....</b>                           | <b>10</b> |
| <b>List of Figures .....</b>                          | <b>11</b> |
| <b>1/ Introduction .....</b>                          | <b>13</b> |
| <b>2/ Installation Procedures .....</b>               | <b>14</b> |
| 2.1. Installing the Board .....                       | 14        |
| 2.2. Chassis Safety Standards .....                   | 15        |
| 2.3. Lithium Battery Replacement .....                | 15        |
| <b>3/ System Specifications .....</b>                 | <b>16</b> |
| 3.1. System Block Diagram .....                       | 16        |
| 3.2. Component Main Data .....                        | 17        |
| 3.3. Environmental Conditions .....                   | 18        |
| 3.4. Standards and Certifications .....               | 18        |
| 3.5. Processor Support .....                          | 20        |
| 3.6. System Memory Support .....                      | 20        |
| 3.6.1. Memory Operating Frequencies .....             | 20        |
| 3.7. On-board Graphics Subsystem .....                | 21        |
| 3.8. Power Supply Voltage .....                       | 21        |
| 3.9. Power Consumption .....                          | 21        |
| <b>4/ Connector Locations .....</b>                   | <b>23</b> |
| 4.1. Top Side .....                                   | 23        |
| 4.2. Rear Side .....                                  | 25        |
| 4.3. Connector Panel Side .....                       | 26        |
| <b>5/ Connector Definitions .....</b>                 | <b>27</b> |
| <b>6/ I/O-Area Connectors .....</b>                   | <b>28</b> |
| 6.1. DP++ Connector (CN18 & CN19) .....               | 28        |
| 6.2. Ethernet Connectors (CN12 & CN13) .....          | 29        |
| 6.3. USB Connectors (I/O Area) .....                  | 30        |
| <b>7/ Internal Connectors .....</b>                   | <b>32</b> |
| 7.1. Power Connector .....                            | 32        |
| 7.1.1. Power Input Wafer (CN5) .....                  | 32        |
| 7.1.2. RTC Battery Power Input Wafer (BAT1) .....     | 33        |
| 7.2. Fan Wafer (CN3) .....                            | 34        |
| 7.3. SATA (Serial ATA) Port 0 Connector (SATA1) ..... | 35        |
| 7.4. HDD / SSD Power Output Wafer (CN8) .....         | 36        |
| 7.5. USB Connectors (Internal) (CN16 & CN17) .....    | 37        |
| 7.6. Audio AMP Output Wafer (CN11 & CN20) .....       | 38        |

|                                                                         |           |
|-------------------------------------------------------------------------|-----------|
| 7.7. Audio Input / Output Pin Header (CN10).....                        | 39        |
| 7.8. Front Panel Pin Header (FP1 & FP2) .....                           | 40        |
| 7.9. Serial COM1 & COM2 Ports (CN23 & CN22).....                        | 42        |
| 7.10. LVDS Panel Connector (CN24).....                                  | 44        |
| 7.11. LVDS Backlight Power Wafer (CN21) .....                           | 46        |
| 7.12. Digital Input / Output Header (CN2).....                          | 47        |
| 7.13. M.2 Key B 3042 Slot (M2B1).....                                   | 48        |
| 7.14. M.2 Key E 2230 Slot (M2E1) .....                                  | 51        |
| 7.15. M.2 Key M 2242 / 2280 Slot (M2M1).....                            | 54        |
| 7.16. Micro SIM Card Holder for M.2 Key B (CN9) .....                   | 57        |
| 7.17. M.2 Key B / M.2 Key E Activity Indicator Header (CN1 & CN4) ..... | 58        |
| 7.18. Switches and Jumpers.....                                         | 59        |
| 7.18.1. LVDS Panel Power Selection (JP1).....                           | 59        |
| 7.18.2. LVDS Backlight Control Selection (JP2).....                     | 60        |
| 7.18.3. LVDS Backlight Enable Selection (JP3) .....                     | 60        |
| 7.18.4. Integrated CNVi Selection for M2E1 (JP4).....                   | 61        |
| 7.18.5. Flash Descriptor Security Override Selection (JP5) .....        | 61        |
| 7.18.6. AT / ATX Power Mode Selection (JP6) .....                       | 61        |
| 7.18.7. Clear CMOS Selection (JP7).....                                 | 62        |
| 7.18.8. USB Power Selection (JP9).....                                  | 62        |
| 7.18.9. MFG Mode Selection (JP10) .....                                 | 63        |
| <b>8/ BIOS.....</b>                                                     | <b>64</b> |
| 8.1. Starting the uEFI BIOS .....                                       | 64        |
| 8.2. Starting the uEFI BIOS .....                                       | 65        |
| 8.2.1. Main Setup Menu .....                                            | 65        |
| 8.2.2. Advanced Setup Menu.....                                         | 67        |
| 8.2.3. Power Setup Menu.....                                            | 83        |
| 8.2.4. Boot Setup Menu .....                                            | 85        |
| 8.2.5. Security Setup Menu .....                                        | 86        |
| 8.2.6. Save & Exit Setup Menu .....                                     | 88        |
| <b>Appendix A: List of Acronyms .....</b>                               | <b>89</b> |
| About Kontron .....                                                     | 90        |

## List of Tables

|                                                                                                            |    |
|------------------------------------------------------------------------------------------------------------|----|
| Table 1: Component Main Data .....                                                                         | 17 |
| Table 2: Environmental Conditions .....                                                                    | 18 |
| Table 3: Standards and Certifications .....                                                                | 18 |
| Table 4: Processor Support.....                                                                            | 20 |
| Table 5: Memory Operating Frequencies.....                                                                 | 20 |
| Table 6: Three-displays Configurations.....                                                                | 21 |
| Table 7: Supply Voltages .....                                                                             | 21 |
| Table 8: Power Consumption.....                                                                            | 22 |
| Table 9: Jumper List.....                                                                                  | 23 |
| Table 10: Top Side Internal Connector Pin Assignment.....                                                  | 23 |
| Table 11: Rear Side Internal Connector Pin Assignment .....                                                | 25 |
| Table 12: Connector Panel Side Connector List.....                                                         | 26 |
| Table 13: Pin Assignment DP++ Connector CN18, CN19 .....                                                   | 28 |
| Table 14: Pin Assignment Ethernet Connector CN12, CN13 .....                                               | 29 |
| Table 15: Pin Assignment USB 3.2 Gen 2 / USB 2.0 Connectors CN14 - Top & Bottom, CN15 - Top & Bottom ..... | 30 |
| Table 16: Pin Assignment CN5 .....                                                                         | 32 |

|                                                           |    |
|-----------------------------------------------------------|----|
| Table 17: Pin Assignment BAT1 .....                       | 33 |
| Table 18: Pin Assignment CN3 .....                        | 34 |
| Table 19: Pin Assignment SATA1 .....                      | 35 |
| Table 20: Pin Assignment CN8 .....                        | 36 |
| Table 21: Pin Assignment CN16, CN17 .....                 | 37 |
| Table 22: Pin Assignment CN11, CN20 .....                 | 38 |
| Table 23: Pin Assignment CN10 .....                       | 39 |
| Table 24: Pin Assignment FP1 .....                        | 40 |
| Table 25: Pin Assignment FP2 .....                        | 40 |
| Table 26: Pin Assignment CN22, CN23 .....                 | 42 |
| Table 27: Signal Description .....                        | 42 |
| Table 28: Pin Assignment CN24 .....                       | 44 |
| Table 29: Pin Assignment CN21 .....                       | 46 |
| Table 30: Pin Assignment CN2 .....                        | 47 |
| Table 31: Pin Assignment M2B1 .....                       | 48 |
| Table 32: Pin Assignment M2E1 .....                       | 51 |
| Table 33: Pin Assignment M2M1 .....                       | 54 |
| Table 34: Pin Assignment CN9 .....                        | 57 |
| Table 35: Pin Assignment CN1 .....                        | 58 |
| Table 36: Pin Assignment CN4 .....                        | 58 |
| Table 37: Pin Assignment JP1 .....                        | 59 |
| Table 38: Pin Assignment JP2 .....                        | 60 |
| Table 39: Pin Assignment JP3 .....                        | 60 |
| Table 40: Pin Assignment JP4 .....                        | 61 |
| Table 41: Pin Assignment JP5 .....                        | 61 |
| Table 42: Pin Assignment JP6 .....                        | 62 |
| Table 43: Pin Assignment JP7 .....                        | 62 |
| Table 44: Pin Assignment JP9 .....                        | 63 |
| Table 45: Pin Assignment JP10 .....                       | 63 |
| Table 46: Hotkeys Table .....                             | 64 |
| Table 47: Main Setup Menu Sub-Screens and Functions ..... | 65 |
| Table 48: List of Acronyms .....                          | 89 |

## List of Figures

|                                                                                   |    |
|-----------------------------------------------------------------------------------|----|
| Figure 1: System Block Diagram 3.5"-SBC-WLU .....                                 | 16 |
| Figure 2: Top Side .....                                                          | 23 |
| Figure 3: Rear Side .....                                                         | 25 |
| Figure 4: Connector Panel Side .....                                              | 26 |
| Figure 5: DP Connector CN18, CN19 .....                                           | 28 |
| Figure 6: Ethernet Connectors CN12, CN13 .....                                    | 29 |
| Figure 7: USB 3.2 Gen 2 Connectors CN14 - Top & Bottom, CN15 - Top & Bottom ..... | 30 |
| Figure 8: USB 2.0 High Speed Cable .....                                          | 30 |
| Figure 9: USB 3.2 High Speed Cable .....                                          | 31 |
| Figure 10: Power Input Wafer CN5 .....                                            | 32 |
| Figure 11: RTC Battery Power Input Wafer BAT1 .....                               | 33 |
| Figure 12: Fan Wafer CN3 .....                                                    | 34 |
| Figure 13: SATA Port 0 Connector SATA1 .....                                      | 35 |
| Figure 14: HDD / SSD Power Output Wafer CN8 .....                                 | 36 |
| Figure 15: USB 2.0 Port 6, 7 Pin Header CN16, Port 8, 9 Pin Header CN17 .....     | 37 |
| Figure 16: Audio AMP Output Wafer CN11 (Right Channel), CN20 (Left Channel) ..... | 38 |
| Figure 17: Audio Input / Output Pin Header CN10 .....                             | 39 |
| Figure 18: Front Panel 1 Pin Header FP1 .....                                     | 40 |
| Figure 19: Front Panel 2 Pin Header FP2 .....                                     | 40 |
| Figure 20: Serial COM CN22, CN23 .....                                            | 42 |
| Figure 21: LVDS Connector CN24 .....                                              | 44 |

|                                                                                           |    |
|-------------------------------------------------------------------------------------------|----|
| Figure 22: LVDS Backlight Power Wafer CN21.....                                           | 46 |
| Figure 23: Digital Input / Output Wafer CN2.....                                          | 47 |
| Figure 24: M.2 Key B 2042 Slot M2B1 .....                                                 | 48 |
| Figure 25: M.2 Key E 2230 Slot M2E1 .....                                                 | 51 |
| Figure 26: M.2 Key M 2242 / 2280 Slot M2M1 .....                                          | 54 |
| Figure 27: Micro SIM Card Holder CN9.....                                                 | 57 |
| Figure 28: M.2 Key B Activity Indicator Header CN1 .....                                  | 58 |
| Figure 29: M.2 Key E Activity Indicator Header CN4.....                                   | 58 |
| Figure 30: Jumper Connector .....                                                         | 59 |
| Figure 31: LVDS Panel Power Selection JP1.....                                            | 59 |
| Figure 32: LVDS Backlight Control Selection JP2.....                                      | 60 |
| Figure 33: LVDS Backlight Enable Selection JP3 .....                                      | 60 |
| Figure 34: Integrated CNVi Selection JP4 .....                                            | 61 |
| Figure 35: Flash Descriptor Security Override Selection JP5.....                          | 61 |
| Figure 36: AT / ATX Power Mode Selection JP6.....                                         | 61 |
| Figure 37: Clear CMOS Selection JP7 .....                                                 | 62 |
| Figure 38: USB Power Selection JP9.....                                                   | 62 |
| Figure 39: MFG Mode Selection JP10.....                                                   | 63 |
| Figure 40: BIOS Main Menu Screen System Data and Time.....                                | 66 |
| Figure 41: BIOS Advanced Menu.....                                                        | 68 |
| Figure 42: BIOS Advanced Menu - Display Configuration.....                                | 69 |
| Figure 43: BIOS Advanced Menu - Super IO Configuration.....                               | 71 |
| Figure 44: BIOS Advanced Menu - Super IO Configuration - Serial Port 1 Configuration..... | 71 |
| Figure 45: BIOS Advanced Menu - Super IO Configuration - Serial Port 2 Configuration..... | 72 |
| Figure 46: BIOS Advanced Menu - CPU Chipset Configuration .....                           | 74 |
| Figure 47: BIOS Advanced Menu - NVMe Configuration.....                                   | 75 |
| Figure 48: BIOS Advanced Menu - SATA Configuration.....                                   | 76 |
| Figure 49: BIOS Advanced Menu - USB Configuration .....                                   | 77 |
| Figure 50: BIOS Advanced Menu - AMT Configuration.....                                    | 78 |
| Figure 51: BIOS Advanced Menu - Trusted Computing .....                                   | 79 |
| Figure 52: BIOS Advanced Menu - H/W Monitor .....                                         | 80 |
| Figure 53: BIOS Advanced Menu - H/W Monitor - Smart FAN Configuration .....               | 80 |
| Figure 54: BIOS Advanced Menu - Network Stack.....                                        | 82 |
| Figure 55: BIOS Power Setup Menu .....                                                    | 83 |
| Figure 56: BIOS Power Setup Menu - WatchDog Timer Configuration.....                      | 83 |
| Figure 57: BIOS Boot Setup Menu .....                                                     | 85 |
| Figure 58: BIOS Security Setup Menu .....                                                 | 86 |
| Figure 59: BIOS Save & Exit Setup Menu.....                                               | 88 |

# 1/ Introduction

This user guide describes the 3.5"-SBC-WLU board made by Kontron. This board will also be denoted 3.5"-SBC-WLU within this user guide.

Use of this user guide implies a basic knowledge of PC-AT hardware and software. This user guide focuses on describing the 3.5"-SBC-WLU board's special features and is not intended to be a standard PC-AT textbook.

New users are recommended to study the short installation procedure stated in the following chapter before switching on the power.

All configuration and setup of the CPU board is either carried out automatically or manually by the user via the BIOS setup menus.

Latest revision of this user guide, datasheet, thermal simulations, BIOS, drivers, BSP's (Board Support Packages), mechanical drawings (2D and 3D) can be downloaded from Kontron's Web Page.

## 2/ Installation Procedures

### 2.1. Installing the Board

#### NOTICE



#### ESD Sensitive Device!

Electrostatic discharge (ESD) can damage equipment and impair electrical circuitry.

- ▶ Wear ESD-protective clothing and shoes
- ▶ Wear an ESD-preventive wrist strap attached to a good earth ground
- ▶ Check the resistance value of the wrist strap periodically (1 MΩ to 10 MΩ)
- ▶ Transport and store the board in its antistatic bag
- ▶ Handle the board at an approved ESD workstation
- ▶ Handle the board only by the edges

To get the board running follow these steps. If the board shipped from KONTRON already has components like RAM and CPU cooler mounted, then skip the relevant steps below.

#### 1. Turn off the PSU (Power Supply Unit)

#### NOTICE

Turn off PSU (Power Supply Unit) completely (no mains power connected to the PSU) or leave the Power Connectors unconnected while configuring the board. Otherwise, components (RAM, LAN cards etc.) might get damaged. Make sure to use +12 V DC single supply only with suitable cable kit and PS-ON# active.

#### NOTICE

The power supply unit shall comply with the requirements as defined in IEC 62368-1 according Clause 6.2.2 to power source category PS2 "Limited Power Source".

#### 2. Insert the DDR4 2400 / 2133 module(s)

Be careful to push the memory module(s) in the slot(s) before locking the tabs.

#### 3. Connecting interfaces

Insert all external cables for hard disk, keyboard etc. A monitor must be connected in order to change BIOS settings.

#### 4. Connect and turn on PSU

Connect PSU to the board by the +12 V 3.0 mm pitch 1x4-pin wafer connector.

#### 5. BIOS setup

Enter the BIOS setup by pressing the <DEL> key during boot up.

Enter "Exit Menu" and Load Setup Defaults.



To clear all BIOS setting, including Password protection, activate "Clear CMOS Jumper" for 10 sec (without power connected).

#### 6. Mounting the board in chassis

#### NOTICE

When mounting the board to chassis etc. please note that the board contains components on both sides of the PCB that can easily be damaged if board is handled without reasonable care. A damaged component can result in malfunction or no function at all.

When fixing the board on a chassis, it is recommended to use screws with an integrated washer and a diameter of > 7 mm. Do not use washers with teeth, as they can damage the PCB and cause short circuits.

## 2.2. Chassis Safety Standards

Before installing the 3.5"-SBC-WLU in the chassis, users must evaluate the end product to ensure compliance with the requirements of the IEC60950-1 safety standard:

- ▶ The board must be installed in a suitable mechanical, electrical and fire enclosure.
- ▶ The system, in its enclosure, must be evaluated for temperature and airflow considerations.
- ▶ The board must be powered by a CSA or UL approved power supply that limits the maximum input current.
- ▶ For interfaces having a power pin such as external power or fan, ensure that the connectors and wires are suitably rated. All connections from and to the product shall be with SELV circuits only.
- ▶ Wires have suitable rating to withstand the maximum available power.
- ▶ The peripheral device enclosure fulfils the IEC60950-1 fire protecting requirements.

## 2.3. Lithium Battery Replacement

If replacing the lithium battery follow the replacement precautions stated in the notification below:

### ⚠ CAUTION

**Danger of explosion if the lithium battery is incorrectly replaced.**

- ▶ Replace only with the same or equivalent type recommended by the manufacturer
- ▶ Dispose of used batteries according to the manufacturer's instructions

**VORSICHT! Explosionsgefahr bei unsachgemäßem Austausch der Batterie.**

- ▶ Ersatz nur durch denselben oder einen vom Hersteller empfohlenen gleichwertigen Typ
- ▶ Entsorgung gebrauchter Batterien nach Angaben des Herstellers

**ATTENTION! Risque d'explosion avec l'échange inadéquat de la batterie.**

- ▶ Remplacement seulement par le même ou un type équivalent recommandé par le producteur
- ▶ L'évacuation des batteries usagées conformément à des indications du fabricant

**PRECAUCION! Peligro de explosión si la batería se sustituye incorrectamente.**

- ▶ Sustituya solamente por el mismo o tipo equivalente recomendado por el fabricante
- ▶ Disponga las baterías usadas según las instrucciones del fabricante

**ADVARESEL! Lithiumbatteri – Eksplosionsfare ved fejlagtig håndtering.**

- ▶ Udskiftning må kun ske med batteri af samme fabrikat og type
- ▶ Levér det brugte batteri tilbage til leverandøren

**ADVARESEL! Eksplosjonsfare ved feilaktig skifte av batteri.**

- ▶ Benytt samme batteritype eller en tilsvarende type anbefalt av apparatfabrikanten
- ▶ Brukte batterier kasseres i henhold til fabrikantens instruksjoner

**VARNING! Explosionsfara vid felaktigt batteribyte.**

- ▶ Använd samma batterityp eller en ekvivalent typ som rekommenderas av apparattillverkaren
- ▶ Kassera använt batteri enligt fabrikantens instruktion


**VAROITUS! Paristo voi räjähtää, jos se on virheellisesti asennettu.**

- ▶ Vaihda paristo ainoastaan lalteil- mistajan suositteluun tyypin
- ▶ Hävitä käytetty paristo valmistajan ohjeiden mukaisesti

## 3/ System Specifications

### 3.1. System Block Diagram

Figure 1: System Block Diagram 3.5"-SBC-WLU



## 3.2. Component Main Data

The table below summarizes the features of the 3.5"-SBC-WLU single board computer.

Table 1: Component Main Data

| System                |                                                                                                                                                                                                                                                                                                                                  |
|-----------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Processor             | <ul style="list-style-type: none"> <li>8th Generation Intel® Core™ U-Series Processors</li> <li>Intel® Celeron® 4000 Series Processors</li> </ul>                                                                                                                                                                                |
| Memory                | <ul style="list-style-type: none"> <li>2x DDR4 SO-DIMM</li> </ul>                                                                                                                                                                                                                                                                |
| Video                 |                                                                                                                                                                                                                                                                                                                                  |
| Display Interface     | <ul style="list-style-type: none"> <li>1x LVDS</li> <li>2x DP++ (on rear)</li> </ul>                                                                                                                                                                                                                                             |
| Multiple Display      | <ul style="list-style-type: none"> <li>Triple</li> </ul>                                                                                                                                                                                                                                                                         |
| Audio                 |                                                                                                                                                                                                                                                                                                                                  |
| Audio Codec           | <ul style="list-style-type: none"> <li>Realtek ALC888S</li> </ul>                                                                                                                                                                                                                                                                |
| Audio Interface       | <ul style="list-style-type: none"> <li>1x Speaker-out (Stereo, 3 W)</li> <li>1x Line-in (by header)</li> <li>1x Line-out (by header)</li> <li>1x Mic-in (by header)</li> </ul>                                                                                                                                                   |
| Network Connection    |                                                                                                                                                                                                                                                                                                                                  |
| Ethernet              | <ul style="list-style-type: none"> <li>2x GbE LAN (RJ45 on rear, Intel® I219-LM, Intel® I210-AT)</li> </ul>                                                                                                                                                                                                                      |
| Peripheral Connection |                                                                                                                                                                                                                                                                                                                                  |
| USB                   | <ul style="list-style-type: none"> <li>4x USB 3.2 Gen 2 (Type A on rear)</li> <li>4x USB 2.0 (by header)</li> </ul>                                                                                                                                                                                                              |
| Serial Port           | <ul style="list-style-type: none"> <li>2x RS232/422/485 (by header)</li> </ul>                                                                                                                                                                                                                                                   |
| Other I/Os            | <ul style="list-style-type: none"> <li>8x DIO (by header)</li> </ul>                                                                                                                                                                                                                                                             |
| Storage & Expansion   |                                                                                                                                                                                                                                                                                                                                  |
| Storage & Expansion   | <ul style="list-style-type: none"> <li>1x SATA 3.0</li> <li>1x Micro SD Cage</li> <li>1x M.2 Key B (Type 2242, w/ PCIe x1 / USB 2.0 / USB 3.2 / UIM)</li> <li>1x M.2 Key E (Type 2230, w/ PCIe x1 / USB 2.0 / CNVi)</li> <li>1x M.2 Key M (Type 2280 / 2242, w/ PCIe x4 / SATA 3.0)</li> <li>1x SIM Cage (Micro type)</li> </ul> |
| Power                 |                                                                                                                                                                                                                                                                                                                                  |
| Input Voltage         | <ul style="list-style-type: none"> <li>DC 12 V</li> </ul>                                                                                                                                                                                                                                                                        |
| Connector             | <ul style="list-style-type: none"> <li>1x4-pin pitch 3.0 mm Wafer</li> </ul>                                                                                                                                                                                                                                                     |
| Firmware              |                                                                                                                                                                                                                                                                                                                                  |
| BIOS                  | <ul style="list-style-type: none"> <li>AMI uEFI BIOS w/ 256 Mb SPI Flash</li> </ul>                                                                                                                                                                                                                                              |
| Watchdog              | <ul style="list-style-type: none"> <li>Programmable WDT to generate system reset event</li> </ul>                                                                                                                                                                                                                                |
| H/W Monitor           | <ul style="list-style-type: none"> <li>Voltages</li> <li>Temperatures</li> </ul>                                                                                                                                                                                                                                                 |

|                                        |                                                                                                                                                                                              |
|----------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>System</b>                          |                                                                                                                                                                                              |
| <b>Real Time Clock</b>                 | ▶ Processor integrated RTC                                                                                                                                                                   |
| <b>Security</b>                        | ▶ TPM 2.0 (Infineon SLB 9665)                                                                                                                                                                |
| <b>System Control &amp; Monitoring</b> |                                                                                                                                                                                              |
| <b>Front Panel Header</b>              | ▶ 1x Header Reset Button, HDD LED & External Speaker<br>▶ 1x Header for Power Button, Power LED & SM bus<br>▶ 1x Header for M.2 Key B activity LED<br>▶ 1x Header for M.2 Key E activity LED |
| <b>Cooling</b>                         |                                                                                                                                                                                              |
| <b>Fan</b>                             | ▶ 1x Wafer for System Fan                                                                                                                                                                    |
| <b>Software</b>                        |                                                                                                                                                                                              |
| <b>OS Support</b>                      | ▶ Windows 10<br>▶ Linux                                                                                                                                                                      |
| <b>Mechanical</b>                      |                                                                                                                                                                                              |
| <b>Dimension (L x W)</b>               | ▶ ECX (146 mm x 105 mm / 5.75" x 4.13")                                                                                                                                                      |

### 3.3. Environmental Conditions

The 3.5"-SBC-WLU is compliant with the following environmental conditions. It is the customer's responsibility to provide sufficient airflow around each of the components to keep them within the allowed temperature range.

**Table 2: Environmental Conditions**

|                              |                                   |
|------------------------------|-----------------------------------|
| <b>Operating Temperature</b> | ▶ 0 °C ~ 60 °C / 32 °F ~ 140 °F   |
| <b>Storage Temperature</b>   | ▶ -20 °C ~ 80 °C / -4 °F ~ 176 °F |
| <b>Humidity</b>              | ▶ 0 % ~ 95 %                      |

### 3.4. Standards and Certifications

The 3.5"-SBC-WLU meets the following standards and certification tests.

**Table 3: Standards and Certifications**

|                   |                                                                                                                                                                                                                                                                                                                          |
|-------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>CE Class B</b> | ▶ EN 55032: 2015 + AC: 2016, Class B<br>▶ CISPR 32: 2015<br>▶ EN 61000-3-2: 2014<br>▶ EN 61000-3-3: 2013<br>▶ EN 55024: 2010 + A1: 2015<br>▶ EN 61000-4-2: 2008<br>▶ EN 61000-4-3: 2006 + A1: 2007 + A2: 2010<br>▶ EN 61000-4-4: 2012<br>▶ EN 61000-4-5: 2014 + A1: 2017<br>▶ EN 61000-4-6: 2013<br>▶ EN 61000-4-8: 2009 |
|-------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|

|                    |                                                                                                         |
|--------------------|---------------------------------------------------------------------------------------------------------|
|                    | ▶ EN 61000-4-11: 2004 + A1: 2017                                                                        |
| <b>FCC Class B</b> | ▶ FCC CFR Title 47 Part 15 Subpart B, Class B<br>▶ ICES-003 Issue 6: 2016 Class B<br>▶ ANSI C63.4: 2014 |

### 3.5. Processor Support

The 3.5"-SBC-WLU is designed to support 8th Generation Intel® Core™ / Celeron® U-Series Processors. The BGA CPU is remounted from factory. Kontron has defined the board versions as listed in the following table, so far all based on Embedded CPUs. Other versions are expected at a later date.

**Table 4: Processor Support**

| Name            | Core # | Speed    | Turbo    | Embedded | Cache | Socket    | TDP  | Tj     |
|-----------------|--------|----------|----------|----------|-------|-----------|------|--------|
| Core™ i7-8665UE | 4      | 1.70 GHz | 4.40 GHz | Yes      | 8M    | FCBGA1528 | 15 W | 100 °C |
| Core™ i5-8365UE | 4      | 1.60 GHz | 4.10 GHz | Yes      | 6M    | FCBGA1528 | 15 W | 100 °C |
| Core™ i3-8145UE | 2      | 2.20 GHz | 3.90 GHz | Yes      | 4M    | FCBGA1528 | 15 W | 100 °C |
| Celeron® 4305UE | 2      | 2.00 GHz | -        | Yes      | 2M    | FCBGA1528 | 15 W | 100 °C |

Sufficient cooling must be applied to the CPU in order to remove the effect as listed as TDP (Thermal Design Power) in above table. The sufficient cooling is also depending on the worst case maximum ambient operating temperature and the actual worst case load of processor.

### 3.6. System Memory Support

The 3.5"-SBC-WLU has two DDR4 SO-DIMM sockets. The sockets support the following memory features:

- ▶ 2x DDR4 SO-DIMM 260-pin
- ▶ Dual-channel with 1x SO-DIMM per channel
- ▶ Up to 64 GB
- ▶ SPD timing supported
- ▶ ECC not supported

The installed DDR4 SO-DIMM should support the Serial Presence Detect (SPD) data structure. This allows the BIOS to read and configure the memory controller for optimal performance. If non-SPD memory is used, the BIOS will attempt to configure the memory settings, but performance and reliability may be impacted, or the board may not be able to boot totally.

#### 3.6.1. Memory Operating Frequencies

In all modes, the frequency of system memory is the lowest frequency of all the memory modules placed in the system. Each memory module's frequency can be determined through the SPD registers on the memory modules.

The table below lists the resulting operating memory frequencies based on the combination of SO-DIMMs and processor.

**Table 5: Memory Operating Frequencies**

| SO-DIMM Type | Module Name | Memory Data Transfer (MT/s) | Processor System Bus Frequency (MHz) | Resulting Memory Clock Frequency (MHz) | Peak Transfer Rate (MB/s) |
|--------------|-------------|-----------------------------|--------------------------------------|----------------------------------------|---------------------------|
| DDR4 2400    | PC4-19200   | 2400                        | 1200                                 | 300                                    | 19200                     |
| DDR4 2133    | PC4-17000   | 2133                        | 1067                                 | 267                                    | 17067                     |

Memory modules have in general a much lower longevity than embedded motherboards, and therefore EOL of modules can be expected several times during lifetime of the motherboard.

As a minimum it is recommend using Kontron memory modules for prototype system(s) in order to prove stability of the system and as for reference.

For volume production you might request to test and qualify other types of RAM. In order to qualify RAM it is recommend configuring 3 systems running RAM Stress Test program in heat chamber at 60° C for a minimum of 24 hours.

### 3.7. On-board Graphics Subsystem

The 3.5"-SBC-WLU supports Intel® UHD Graphics technology for high quality graphics capabilities. All 3.5"-SBC-WLU versions support triple displays pipes.

Triple displays can be used simultaneously and be used to implement independent or cloned display configuration.

**Table 6: Three-displays Configurations**

| Display 1 | Display 2 | Display 3 | Max. Resolution (Px) at 60 Hz |             |             |
|-----------|-----------|-----------|-------------------------------|-------------|-------------|
|           |           |           | Display 1                     | Display 2   | Display 3   |
| LVDS      | DP++      | DP++      | 1920 x 1200                   | 4096 x 2304 | 4096 x 2304 |

### 3.8. Power Supply Voltage

In order to ensure safe operation of the board, the input power supply must monitor the supply voltage and shut down if the supply is out of range – refer to the actual power supply specification. Please note, in order to keep the power consumption to a minimal level, boards do not implement a guaranteed minimum load. The 3.5"-SBC-WLU board must be powered through the 3.0 mm pitch 1x4-pin wafer connector from a DC 12 V power supply.

#### NOTICE

Hot Plugging power supply is not supported. Hot plugging might damage the board.

The requirements to the supply voltages are as follows:

**Table 7: Supply Voltages**

| Supply | Min.   | Max.   | Note                     |
|--------|--------|--------|--------------------------|
| +12 V  | 11.4 V | 12.6 V | Should be ±5 % tolerance |

### 3.9. Power Consumption

The power consumption is measured under the following software and hardware condition.

- ▶ 3.5"-SBC-WLU with Intel® Core™ i7-8665UE processor (Quad Core @ 1.8 GHz)
- ▶ Memory: 2x 4 GByte DDR4
- ▶ Storage: Transcend TS128GMTE550T M.2 PCIe 128 GByte SSD
- ▶ Operating System: Windows 10 Enterprise LTSC 1809 (17763.107)

The power consumption in different modes is as follows:

**Table 8: Power Consumption**

| Power Status       | Input Voltage | Power Consumption |
|--------------------|---------------|-------------------|
| Boot (Peak)        | +12 V         | 73.68 W           |
| Full Run (S0)      | +12 V         | 23.28 W           |
| Sleep (S3)         | +12 V         | 262.2 mW          |
| Shutdown (S4 / S5) | +12 V         | 211.32 mW         |
| Shutdown (PSM)     | +12 V         | 54.12 mW          |

## 4/ Connector Locations

### 4.1. Top Side

Figure 2: Top Side




Table 9: Jumper List

| Item | Designation | Description                                  | See Chapter |
|------|-------------|----------------------------------------------|-------------|
| 1    | JP1         | LVDS Panel Power Selection                   | 7.18.1      |
| 2    | JP2         | LVDS Backlight Control Selection             | 7.18.2      |
| 3    | JP3         | LVDS Backlight Enable Selection              | 7.18.3      |
| 4    | JP4         | Integrated CNVi Selection for M2E1           | 7.18.4      |
| 5    | JP5         | Flash Descriptor Security Override Selection | 7.18.5      |
| 6    | JP6         | AT / ATX Power Mode Selection                | 7.18.6      |
| 7    | JP7         | Clear CMOS Selection                         | 7.18.7      |
| 8    | JP9         | USB Power Selection                          | 7.18.8      |
| 9    | JP10        | MFG Mode Selection                           | 7.18.9      |

Table 10: Top Side Internal Connector Pin Assignment

| Item | Designation | Description                        | See Chapter |
|------|-------------|------------------------------------|-------------|
| 10   | BAT1        | RTC Power Input Wafer              | 7.1.2       |
| 11   | CN1         | Activity Indicator Header for M2B1 | 7.17        |
| 12   | CN2         | SDXC / DIO Header                  | 7.12        |

| Item | Designation | Description                          | See Chapter |
|------|-------------|--------------------------------------|-------------|
| 13   | CN3         | FAN Wafer                            | 7.2         |
| 14   | CN4         | Activity Indicator Header for M2E1   | 7.17        |
| 15   | CN5         | +12 V DC Power Input Wafer           | 7.1.1       |
| 16   | CN8         | +5 V DC HDD / SSD Power Output Wafer | 7.4         |
| 17   | CN9         | Micro SIM Card Holder for M2B1       | 7.16        |
| 18   | CN10        | Audio Input / Output Header          | 7.7         |
| 19   | CN11        | Right Channel Audio AMP Output Wafer | 7.6         |
| 20   | CN16        | USB 2.0 Port 6, 7 Header             | 7.5         |
| 21   | CN17        | USB 2.0 Port 8, 9 Header             | 7.5         |
| 22   | CN20        | Left Channel Audio AMP Output Wafer  | 7.6         |
| 23   | DIMM1       | DDR4 Channel 0 SO-DIMM Slot          | 3.6         |
| 24   | DIMM2       | DDR4 Channel 1 SO-DIMM Slot          | 3.6         |
| 25   | FP1         | Front Panel Header 1                 | 7.8         |
| 26   | FP2         | Front Panel Header 2                 | 7.8         |
| 27   | M2B1        | M.2 Key B 3042 Slot                  | 7.13        |
| 28   | M2E1        | M.2 Key E 2230 Slot                  | 7.14        |
| 29   | M2M1        | M.2 Key M 2242 / 2280 Slot           | 7.15        |
| 30   | SATA1       | SATA Port 0 Connector                | 7.3         |

## 4.2. Rear Side

Figure 3: Rear Side




Table 11: Rear Side Internal Connector Pin Assignment

| Item | Designation | Description                  | See Chapter |
|------|-------------|------------------------------|-------------|
| 1    | CN21        | LVDS Backlight Power Wafer   | 7.11        |
| 2    | CN22        | RS232/422/485 COM2 Wafer     | 7.9         |
| 3    | CN23        | RS232/422/485 COM1 Wafer     | 7.9         |
| 4    | CN24        | 24-bit / 2-ch LVDS Connector | 7.10        |

### 4.3. Connector Panel Side

Figure 4: Connector Panel Side




Table 12: Connector Panel Side Connector List

| Item | Designation | Description                              | See Chapter |
|------|-------------|------------------------------------------|-------------|
| 1    | CN12        | GbE LAN1 RJ45 Connector                  | 6.2         |
| 2    | CN13        | GbE LAN2 RJ45 Connector                  | 6.2         |
| 3    | CN14        | USB 3.2 Gen 2 Port 1, 2 Type A Connector | 6.3         |
| 4    | CN15        | USB 3.2 Gen 2 Port 3, 4 Type A Connector | 6.3         |
| 5    | CN18        | DP++ Port 2 Connector                    | 6.1         |
| 6    | CN19        | DP++ Port 1 Connector                    | 6.1         |

## 5/ Connector Definitions

The following defined terms are used within this user guide to give more information concerning the pin assignment and to describe the connector's signals.

| Defined Term | Description                                                                                                           |
|--------------|-----------------------------------------------------------------------------------------------------------------------|
| Pin          | Shows the pin numbers in the connector                                                                                |
| Signal       | The abbreviated name of the signal at the current pin<br>The notation "XX#" states that the signal "XX" is active low |
| Note         | Special remarks concerning the signal                                                                                 |
| Designation  | Type and number of item described                                                                                     |
| See Chapter  | Number of the chapter within this user guide containing a detailed description                                        |

The abbreviation TBD is used for specifications that are not available yet or which are not sufficiently specified by the component vendors.

## 6/ I/O-Area Connectors

### 6.1. DP++ Connector (CN18 & CN19)

The DP++ (Dual-mode DisplayPort) connectors are based on standard DP female port.

Figure 5: DP Connector CN18, CN19




Table 13: Pin Assignment DP++ Connector CN18, CN19

| Pin | Signal    | Description                                                       | Note |
|-----|-----------|-------------------------------------------------------------------|------|
| 1   | ML_Lane0p | DisplayPort Lane 0 transmitter differential pair (+)              |      |
| 2   | GND       | Ground                                                            |      |
| 3   | ML_Lane0n | DisplayPort Lane 0 transmitter differential pair (-)              |      |
| 4   | ML_Lane1p | DisplayPort Lane 1 transmitter differential pair (+)              |      |
| 5   | GND       | Ground                                                            |      |
| 6   | ML_Lane1n | DisplayPort Lane 1 transmitter differential pair (-)              |      |
| 7   | ML_Lane2p | DisplayPort Lane 2 transmitter differential pair (+)              |      |
| 8   | GND       | Ground                                                            |      |
| 9   | ML_Lane2n | DisplayPort Lane 2 transmitter differential pair (-)              |      |
| 10  | ML_Lane3p | DisplayPort Lane 3 transmitter differential pair (+)              |      |
| 11  | GND       | Ground                                                            |      |
| 12  | ML_Lane3n | DisplayPort Lane 3 transmitter differential pair (-)              |      |
| 13  | Config1   | Connected to ground, either directly or through a pulldown device |      |
| 14  | Config2   | Connected to ground, either directly or through a pulldown device |      |
| 15  | AUX_CHp   | DisplayPort Auxiliary channel differential pair (+)               |      |
| 16  | GND       | Ground                                                            |      |
| 17  | AUX_CHn   | DisplayPort Auxiliary channel differential pair (-)               |      |
| 18  | Hot_Plug  | DisplayPort hot plug detect                                       |      |
| 19  | GND       | Ground                                                            |      |
| 20  | DP_PWR    | Power for connector                                               |      |

## 6.2. Ethernet Connectors (CN12 & CN13)

The 3.5"-SBC-WLU supports two channels of 10/100/1000 Mbit Ethernet, which are based Intel® I219-LM and Intel® I210-AT controller respectively.

In order to achieve the specified performance of the Ethernet port, Category 5 twisted pair cables must be used with 10/100 MByte and Category 5E, 6 or 6E with 1 Gbit LAN networks.

The signals for the Ethernet ports are as follows:

Figure 6: Ethernet Connectors CN12, CN13




Table 14: Pin Assignment Ethernet Connector CN12, CN13

| Pin | Signal | Note |
|-----|--------|------|
| 1   | TX1+   |      |
| 2   | TX1-   |      |
| 3   | TX2+   |      |
| 4   | TX3+   |      |
| 5   | TX3-   |      |
| 6   | TX2-   |      |
| 7   | TX4+   |      |
| 8   | TX4-   |      |

### Signal Description

| Signal      | Description                                                                                                                                                                                                                                      |
|-------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| TX1+ / TX1- | In MDI mode, this is the first pair in 1000Base-T, i.e. the BI_DA+/- pair, and is the transmit pair in 10Base-T and 100Base-TX. In MDI crossover mode, this pair acts as the BI_DB+/- pair, and is the receive pair in 10Base-T and 100Base-TX.  |
| TX2+ / TX2- | In MDI mode, this is the second pair in 1000Base-T, i.e. the BI_DB+/- pair, and is the receive pair in 10Base-T and 100Base-TX. In MDI crossover mode, this pair acts as the BI_DA+/- pair, and is the transmit pair in 10Base-T and 100Base-TX. |
| TX3+ / TX3- | In MDI mode, this is the third pair in 1000Base-T, i.e. the BI_DC+/- pair. In MDI crossover mode, this pair acts as the BI_DD+/- pair.                                                                                                           |
| TX4+ / TX4- | In MDI mode, this is the fourth pair in 1000Base-T, i.e. the BI_DD+/- pair. In MDI crossover mode, this pair acts as the BI_DC+/- pair.                                                                                                          |

'MDI' – media dependent Interface

### 6.3. USB Connectors (I/O Area)

The external I/O connector panel supports two dual USB 3.2 Gen 2 connectors.



USB 3.2 Gen 2 ports are backward compatible with USB 2.0.

Figure 7: USB 3.2 Gen 2 Connectors CN14 - Top & Bottom, CN15 - Top & Bottom



Table 15: Pin Assignment USB 3.2 Gen 2 / USB 2.0 Connectors CN14 - Top & Bottom, CN15 - Top & Bottom


| Pin | Signal    | Description                                     | Note |
|-----|-----------|-------------------------------------------------|------|
| 1   | +USB_VCC* | +5 V power supply for USB device                |      |
| 2   | USB_D-    | USB 2.0 differential pair (-)                   |      |
| 3   | USB_D+    | USB 2.0 differential pair (+)                   |      |
| 4   | GND       | Ground                                          |      |
| 5   | USB_RX-   | USB 3.2 Gen 2 receiver differential pair (-)    |      |
| 6   | USB_RX+   | USB 3.2 Gen 2 receiver differential pair (+)    |      |
| 7   | GND       | Ground                                          |      |
| 8   | USB_TX-   | USB 3.2 Gen 2 transmitter differential pair (-) |      |
| 9   | USB_TX+   | USB 3.2 Gen 2 transmitter differential pair (+) |      |



\* The power source of +USBVCC can be selected by JP9.


For HiSpeed rates it is required to use a USB cable, which is specified in USB 2.0 standard:

Figure 8: USB 2.0 High Speed Cable



For USB 3.2 Gen 2 cabling it is required to use only HiSpeed USB cable, specified in USB 3.2 standard:

Figure 9: USB 3.2 High Speed Cable



## 7/ Internal Connectors

### 7.1. Power Connector

Power connector must be used to supply the board with +12 VDC ( $\pm 5\%$ ).

#### NOTICE

Hot plugging any of the power connector is not allowed.

Hot plugging might damage the board. In other words, turn off main supply etc. to make sure all the power lines are turned off when connecting to the motherboard.

#### 7.1.1. Power Input Wafer (CN5)

The 1x4-pin 3.0 mm pitch power input wafer provides +12 V DC to the board.

Figure 10: Power Input Wafer CN5




Table 16: Pin Assignment CN5

| Pin                        | Signal        | Description | Note |
|----------------------------|---------------|-------------|------|
| 1                          | +12Vin        | Power +12 V |      |
| 2                          | GND           | Ground      |      |
| 3                          | GND           | Ground      |      |
| 4                          | +12Vin        | Power +12 V |      |
| <b>Connector Type</b>      |               |             |      |
| B2W, 1x4-pin, 3.0 mm pitch |               |             |      |
| <b>Mating Connector</b>    |               |             |      |
| Vendor                     | PINREX        |             |      |
| Housing Model No.          | 733-75-M104B6 |             |      |
| Terminal Model No.         | 733-70-FT0006 |             |      |

### 7.1.2. RTC Battery Power Input Wafer (BAT1)

The 1x2-pin 1.25 mm pitch RTC battery power input wafer is intended to be connected to the battery. The battery provides power to the system clock to retain the time when power is turn off.

Figure 11: RTC Battery Power Input Wafer BAT1



Table 17: Pin Assignment BAT1

| Pin                         | Signal        | Description                          | Note |
|-----------------------------|---------------|--------------------------------------|------|
| 1                           | +VRTC         | Real-time clock backup battery input |      |
| 2                           | GND           | Ground                               |      |
| <b>Connector Type</b>       |               |                                      |      |
| B2W, 1x2-pin, 1.25 mm pitch |               |                                      |      |
| <b>Mating Connector</b>     |               |                                      |      |
| Vendor                      | PINREX        |                                      |      |
| Housing Model No.           | 712-75-02W001 |                                      |      |
| Terminal Model No.          | 712-70-T00001 |                                      |      |

## 7.2. Fan Wafer (CN3)

The 1x4-pin 2.54 mm pitch system fan wafer (CN3) is used for the connection of the fan for the processor or system.

Figure 12: Fan Wafer CN3




Table 18: Pin Assignment CN3

| Pin                         | Signal | Description                                                                                 | Note     |
|-----------------------------|--------|---------------------------------------------------------------------------------------------|----------|
| 1                           | GND    | Power supply ground signal                                                                  |          |
| 2                           | +12V   | +12 V power supply for fan                                                                  | 1 A max. |
| 3                           | SENSE  | Sense input signal from the fan, for rotation speed supervision RPM (Rotations Per Minute). |          |
| 4                           | PWM    | PWM output signal for FAN speed control                                                     |          |
| <b>Connector Type</b>       |        |                                                                                             |          |
| B2W, 1x4-pin, 2.54 mm pitch |        |                                                                                             |          |

### 7.3. SATA (Serial ATA) Port 0 Connector (SATA1)

The SATA connector supplies the data connection for the SATA hard disk and is SATA 3.0 compatible.

Figure 13: SATA Port 0 Connector SATA1



Table 19: Pin Assignment SATA1

| Pin                         | Signal        | Description                                   | Note |
|-----------------------------|---------------|-----------------------------------------------|------|
| 1                           | GND           | Ground                                        |      |
| 2                           | TX+           | Host transmitter differential signal pair (+) |      |
| 3                           | TX-           | Host transmitter differential signal pair (-) |      |
| 4                           | GND           | Ground                                        |      |
| 5                           | RX-           | Host receiver differential signal pair (-)    |      |
| 6                           | RX+           | Host receiver differential signal pair (+)    |      |
| 7                           | GND           | Ground                                        |      |
| <b>Connector Type</b>       |               |                                               |      |
| B2W, 1x7-pin, 1.27 mm pitch |               |                                               |      |
| <b>Mating Connector</b>     |               |                                               |      |
| Vendor                      | WINWIN        |                                               |      |
| Model No.                   | WATC-07DLPO2U |                                               |      |

## 7.4. HDD / SSD Power Output Wafer (CN8)

The 1x4-pin 2.0 mm pitch HDD / SSD power output wafer provides power to the SATA hard disk.

Figure 14: HDD / SSD Power Output Wafer CN8



Table 20: Pin Assignment CN8

| Pin                        | Signal        | Description                     | Note     |
|----------------------------|---------------|---------------------------------|----------|
| 1                          | +5V           | +5 V power supply for HDD / SSD | 1 A max. |
| 2                          | GND           | Ground                          |          |
| 3                          | GND           | Ground                          |          |
| 4                          | +5V           | +5 V power supply for HDD / SSD | 1 A max. |
| <b>Connector Type</b>      |               |                                 |          |
| B2W, 1x4-pin, 2.0 mm pitch |               |                                 |          |
| <b>Mating Connector</b>    |               |                                 |          |
| Vendor                     | PINREX        |                                 |          |
| Housing Model No.          | 721-75-04W009 |                                 |          |
| Terminal Model No.         | 721-70-T00009 |                                 |          |

## 7.5. USB Connectors (Internal) (CN16 & CN17)

The 10-pin 2.54 mm pitch USB port pin header CN16 & CN17 supports two USB 2.0 ports each.

Figure 15: USB 2.0 Port 6, 7 Pin Header CN16, Port 8, 9 Pin Header CN17




Table 21: Pin Assignment CN16, CN17

| Pin                         | Signal        | Description                                                     | Note     |
|-----------------------------|---------------|-----------------------------------------------------------------|----------|
| 1                           | +USBVCC*      | 5 V supply. SB5V is supplied during power down to allow wakeup. | 1 A max. |
| 2                           | +USBVCC*      | 5 V supply. SB5V is supplied during power down to allow wakeup. | 1 A max. |
| 3                           | USB_DA-       | USB 2.0 differential pair (-) for channel A                     |          |
| 4                           | USB_DB-       | USB 2.0 differential pair (-) for channel B                     |          |
| 5                           | USB_DA+       | USB 2.0 differential pair (+) for channel A                     |          |
| 6                           | USB_DB+       | USB 2.0 differential pair (+) for channel B                     |          |
| 7                           | GND           | Ground                                                          |          |
| 8                           | GND           | Ground                                                          |          |
| 9                           | KEY           |                                                                 |          |
| 10                          | GND           | Ground                                                          |          |
| <b>Connector Type</b>       |               |                                                                 |          |
| B2W, 2x5-pin, 2.54 mm pitch |               |                                                                 |          |
| <b>Mating Connector</b>     |               |                                                                 |          |
| Vendor                      | PINREX        |                                                                 |          |
| Housing Model No.           | 741-75-205B01 |                                                                 |          |
| Terminal Model No.          | 741-70-FT0001 |                                                                 |          |



\* The power source of +USBVCC for CN16 and CN17 can be selected by JP9.

## 7.6. Audio AMP Output Wafer (CN11 & CN20)

The Speaker audio-out interface is available through the 2-pin 2.0 mm pitch wafers CN11 and CN20. These outputs are shared with the audio output (Line-out) signals of the audio pin header CN10.

Figure 16: Audio AMP Output Wafer CN11 (Right Channel), CN20 (Left Channel)




Table 22: Pin Assignment CN11, CN20

| Pin                        | Signal        | Description        | Note |
|----------------------------|---------------|--------------------|------|
| 1                          | Speaker+      | Speaker output (+) |      |
| 2                          | Speaker-      | Speaker output (-) |      |
| <b>Connector Type</b>      |               |                    |      |
| B2W, 1x2-pin, 2.0 mm pitch |               |                    |      |
| <b>Mating Connector</b>    |               |                    |      |
| Vendor                     | PINREX        |                    |      |
| Housing Model No.          | 721-75-02W009 |                    |      |
| Terminal Model No.         | 721-70-T00009 |                    |      |

## 7.7. Audio Input / Output Pin Header (CN10)

The audio input / output pin header provides audio output (Line-Out), audio input (Line-In) and microphone (Mic-In) signals through the 12-pin 2.54 mm pitch wafer CN10. The audio output signals are shared with those of the speaker connectors CN11 & CN20.

Figure 17: Audio Input / Output Pin Header CN10




Table 23: Pin Assignment CN10

| Pin                         | Signal        | Description                           | Note |
|-----------------------------|---------------|---------------------------------------|------|
| 1                           | MIC-In_L      | Microphone input left channel signal  |      |
| 2                           | MIC-In_R      | Microphone input right channel signal |      |
| 3                           | MIC-In_JD#    | Microphone jack detection             |      |
| 4                           | GND           | Ground                                |      |
| 5                           | Line-In_L     | Audio input left channel signal       |      |
| 6                           | Line-In_R     | Audio input right channel signal      |      |
| 7                           | Line-In_JD#   | Audio input jack detection            |      |
| 8                           | GND           | Ground                                |      |
| 9                           | Line-Out_L    | Audio output left channel signal      |      |
| 10                          | Line-Out_R    | Audio output right channel signal     |      |
| 11                          | Line-Out_JD#  | Audio output jack detection           |      |
| 12                          | GND           | Ground                                |      |
| <b>Connector Type</b>       |               |                                       |      |
| B2W, 2x6-pin, 2.54 mm pitch |               |                                       |      |
| <b>Mating Connector</b>     |               |                                       |      |
| Vendor                      | PINREX        |                                       |      |
| Housing Model No.           | 741-75-206B01 |                                       |      |
| Terminal Model No.          | 741-70-FT0001 |                                       |      |

## 7.8. Front Panel Pin Header (FP1 & FP2)

The 8-pin 2.54 mm pitch front panel pin header FP1 supplies signals for the reset button, storage LED and system warning speaker.

The 10-pin 2.54 mm pitch front panel pin header FP2 supplies signals for the power button, power LED, and SM Bus.

Figure 18: Front Panel 1 Pin Header FP1




Table 24: Pin Assignment FP1

| Pin                         | Signal             | Description                                                                                       | Note |
|-----------------------------|--------------------|---------------------------------------------------------------------------------------------------|------|
| 1                           | Reset Button +     | System reset button (+)                                                                           |      |
| 2                           | Speaker +          | External system warning speaker (+)                                                               |      |
| 3                           | Reset Button -     | System reset button (-)                                                                           |      |
| 4                           | -                  | No connection                                                                                     |      |
| 5                           | HDD LED +          | HDD activity LED (+). The LED lights up or flashes when data is ready from or written to the HDD. |      |
| 6                           | Internal Speaker - | Internal system warning speaker (-)                                                               |      |
| 7                           | HDD LED -          | HDD activity LED (-).                                                                             |      |
| 8                           | Speaker -          | External system warning speaker (-)                                                               |      |
| <b>Connector Type</b>       |                    |                                                                                                   |      |
| B2W, 2x4-pin, 2.54 mm pitch |                    |                                                                                                   |      |
| <b>Mating Connector</b>     |                    |                                                                                                   |      |
| Vendor                      | PINREX             |                                                                                                   |      |
| Housing Model No.           | 741-75-204B01      |                                                                                                   |      |
| Terminal Model No.          | 741-70-FT0001      |                                                                                                   |      |



Internal Buzzer is enabled when Pin6-8 is shorted.

Figure 19: Front Panel 2 Pin Header FP2




Table 25: Pin Assignment FP2

| Pin | Signal      | Description                                                    | Note |
|-----|-------------|----------------------------------------------------------------|------|
| 1   | Power LED + | System Power LED (+). The LED lights up when users turn on the |      |

| Pin                                                                                                       | Signal         | Description                                                                                                                                                                                                                                                 | Note |
|-----------------------------------------------------------------------------------------------------------|----------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------|
|                                                                                                           |                | system power, and blinks when the system is in sleep mode.                                                                                                                                                                                                  |      |
| 2                                                                                                         | Power Button + | System power button (+). Pressing the power button turns the system on or puts the system in sleep or soft-off mode depending on the operating system settings. Pressing the power switch for more than four seconds while the system turns from ON to OFF. |      |
| 3                                                                                                         | -              | No connection                                                                                                                                                                                                                                               |      |
| 4                                                                                                         | Power Button - | System power button (-).                                                                                                                                                                                                                                    |      |
| 5                                                                                                         | Power LED -    | System Power LED (-).                                                                                                                                                                                                                                       |      |
| 6                                                                                                         | -              | No connection                                                                                                                                                                                                                                               |      |
| 7                                                                                                         | -              | No connection                                                                                                                                                                                                                                               |      |
| 8                                                                                                         | SMBus Data     | System management bus bidirectional data line                                                                                                                                                                                                               |      |
| 9                                                                                                         | GND            | Ground                                                                                                                                                                                                                                                      |      |
| 10                                                                                                        | SMBus Clock    | System management bus bidirectional clock line                                                                                                                                                                                                              |      |
| <b>Connector Type</b>                                                                                     |                |                                                                                                                                                                                                                                                             |      |
| B2W, 2x5-pin, 2.54 mm pitch                                                                               |                |                                                                                                                                                                                                                                                             |      |
| <b>Mating Connector</b>                                                                                   |                |                                                                                                                                                                                                                                                             |      |
| <b>Vendor</b> PINREX<br><b>Housing Model No.</b> 741-75-205B01<br><b>Terminal Model No.</b> 741-70-FT0001 |                |                                                                                                                                                                                                                                                             |      |

## 7.9. Serial COM1 & COM2 Ports (CN23 & CN22)

The 10-pin 1.25 mm pitch serial COM wafer CN22 and CN23 provide RS232/422/485 connections.

Figure 20: Serial COM CN22, CN23




Table 26: Pin Assignment CN22, CN23

| Pin                          | RS232 Signal  | RS422 Signal | Half Duplex RS485 Signal | Full Duplex RS485 Signal | Note        |
|------------------------------|---------------|--------------|--------------------------|--------------------------|-------------|
| 1                            | DCD           | TX-          | DATA-                    | TX-                      |             |
| 2                            | DSR           | -            | -                        | -                        |             |
| 3                            | RXD           | TX+          | DATA+                    | TX+                      |             |
| 4                            | RTS           | -            | -                        | -                        |             |
| 5                            | TXD           | RX+          | -                        | RX+                      |             |
| 6                            | CTS           | -            | -                        | -                        |             |
| 7                            | DTR           | RX-          | -                        | RX-                      |             |
| 8                            | RI            | -            | -                        | -                        |             |
| 9                            | GND           | GND          | GND                      | GND                      |             |
| 10                           | +5V           | +5V          | +5V                      | +5V                      | 500 mA max. |
| <b>Connector Type</b>        |               |              |                          |                          |             |
| B2W, 1x10-pin, 1.25 mm pitch |               |              |                          |                          |             |
| <b>Mating Connector</b>      |               |              |                          |                          |             |
| Vendor                       | PINREX        |              |                          |                          |             |
| Housing Model No.            | 712-75-10W001 |              |                          |                          |             |
| Terminal Model No.           | 712-70-T00001 |              |                          |                          |             |

Table 27: Signal Description

| Signal | Description                                                                                                                                                                                       |
|--------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| TXD    | Transmitted Data, sends data to the communications link. The signal is set to the marking state (-12 V) on hardware reset when the transmitter is empty or when loop mode operation is initiated. |
| RXD    | Received Data, receives data from the communications link.                                                                                                                                        |
| DTR    | Data Terminal Ready, indicates to the modem etc. that the on-board UART is ready to establish communication link.                                                                                 |
| DSR    | Data Set Ready, indicates that the modem etc. is ready to establish a communications link.                                                                                                        |
| RTS    | Request To Send, indicates to the modem etc. that the on-board UART is ready to                                                                                                                   |

| Signal | Description                                                                                     |
|--------|-------------------------------------------------------------------------------------------------|
|        | exchange data.                                                                                  |
| CTS    | Clear To Send, indicates that the modem or data set is ready to exchange data.                  |
| DCD    | Data Carrier Detect, indicates that the modem or data set has detected the data carrier.        |
| RI     | Ring Indicator, indicates that the modem has received a ringing signal from the telephone line. |
| TX+/-  | Transmitted Data differential pair sends data to the communications link.                       |
| RX+/-  | Received Data differential pair receives data from the communications link.                     |
| GND    | Power Supply GND signal                                                                         |

## 7.10. LVDS Panel Connector (CN24)

The 30-pole 1.0 mm pitch JAE connector provides 24-bit, 2-channel LVDS panel connection.

Figure 21: LVDS Connector CN24




Table 28: Pin Assignment CN24

| Pin | Signal     | Description                                 | Note |
|-----|------------|---------------------------------------------|------|
| 1   | LVDSA_TX0- | LVDS Channel A Data 0 differential pair (-) |      |
| 2   | LVDSA_TX0+ | LVDS Channel A Data 0 differential pair (+) |      |
| 3   | LVDSA_TX1- | LVDS Channel A Data 1 differential pair (-) |      |
| 4   | LVDSA_TX1+ | LVDS Channel A Data 1 differential pair (+) |      |
| 5   | LVDSA_TX2- | LVDS Channel A Data 2 differential pair (-) |      |
| 6   | LVDSA_TX2+ | LVDS Channel A Data 2 differential pair (+) |      |
| 7   | GND        | Ground                                      |      |
| 8   | LVDSA_CLK- | LVDS Channel A clock differential pair (-)  |      |
| 9   | LVDSA_CLK+ | LVDS Channel A clock differential pair (+)  |      |
| 10  | LVDSA_TX3- | LVDS Channel A Data 3 differential pair (-) |      |
| 11  | LVDSA_TX3+ | LVDS Channel A Data 3 differential pair (+) |      |
| 12  | LVDSB_TX0- | LVDS Channel B Data 0 differential pair (-) |      |
| 13  | LVDSB_TX0+ | LVDS Channel B Data 0 differential pair (+) |      |
| 14  | GND        | Ground                                      |      |
| 15  | LVDSB_TX1- | LVDS Channel B Data 1 differential pair (-) |      |
| 16  | LVDSB_TX1+ | LVDS Channel B Data 1 differential pair (+) |      |
| 17  | GND        | Ground                                      |      |
| 18  | LVDSB_TX2- | LVDS Channel B Data 2 differential pair (-) |      |
| 19  | LVDSB_TX2+ | LVDS Channel B Data 2 differential pair (+) |      |
| 20  | LVDSB_CLK- | LVDS Channel B clock differential pair (-)  |      |
| 21  | LVDSB_CLK+ | LVDS Channel B clock differential pair (+)  |      |

| Pin                         | Signal     | Description                                 | Note        |
|-----------------------------|------------|---------------------------------------------|-------------|
| 22                          | LVDSB_TX3- | LVDS Channel B Data 3 differential pair (-) |             |
| 23                          | LVDSB_TX3+ | LVDS Channel B Data 3 differential pair (+) |             |
| 24                          | GND        | Ground                                      |             |
| 25                          | DDC_DATA   | DDC channel Data                            |             |
| 26                          | VDDEN      | Output Display Enable                       |             |
| 27                          | DDC_CLK    | DDC Channel Clock                           |             |
| 28                          | VPNL *     | +3.3 V / +5 V panel power supply            | 500 mA max. |
| 29                          | VPNL *     | +3.3 V / +5 V panel power supply            | 500 mA max. |
| 30                          | VPNL *     | +3.3 V / +5 V panel power supply            | 500 mA max. |
| <b>Connector Type</b>       |            |                                             |             |
| B2W, 1x30-pin, 1.0 mm pitch |            |                                             |             |
| <b>Mating Connector</b>     |            |                                             |             |
| Vendor                      | JAE        |                                             |             |
| Model No.                   | FI-X30HL   |                                             |             |




---

\* Panel Power can be selected by JP1.

---

## 7.11. LVDS Backlight Power Wafer (CN21)

The 7-pin 1.25 mm pitch wafer CN21 provides power supply for flat panel and its backlight inverter.

Figure 22: LVDS Backlight Power Wafer CN21




Table 29: Pin Assignment CN21

| Pin                         | Signal        | Description                                              | Note        |
|-----------------------------|---------------|----------------------------------------------------------|-------------|
| 1                           | BL_EN***      | Backlight Enable signal                                  |             |
| 2                           | GND           | Ground                                                   |             |
| 3                           | +VBKLT**      | +5 V / +12 V backlight power supply                      | 750 mA max. |
| 4                           | +VBKLT**      | +5 V / +12 V backlight power supply                      | 750 mA max. |
| 5                           | GND           | Ground                                                   |             |
| 6                           | BL_ADJ_VOL*   | Backlight Adjustment Voltage signal                      |             |
| 7                           | BL_ADJ_PWM*   | Backlight Adjustment PWM (Pulse Width Modulation) signal |             |
| <b>Connector Type</b>       |               |                                                          |             |
| B2W, 1x7-pin, 1.25 mm pitch |               |                                                          |             |
| <b>Mating Connector</b>     |               |                                                          |             |
| Vendor                      | PINREX        |                                                          |             |
| Housing Model No.           | 712-75-07W001 |                                                          |             |
| Terminal Model No.          | 712-70-T00001 |                                                          |             |



\* BL\_ADJ can be selected by JP2.



\*\* Backlight Power can be selected by JP1.



\*\*\* BL\_EN can be selected by JP3.

## 7.12. Digital Input / Output Header (CN2)

The header CN2 supports 8-bit digital input / output signals to provide powering-on function of the connected devices.

Figure 23: Digital Input / Output Wafer CN2




Table 30: Pin Assignment CN2

| Pin                          | Signal        | Description                      | Note        |
|------------------------------|---------------|----------------------------------|-------------|
| 1                            | +5V           | +5 V power supply                | 500 mA max. |
| 2                            | DIO_0         | Digital input / output channel 0 |             |
| 3                            | DIO_1         | Digital input / output channel 1 |             |
| 4                            | DIO_2         | Digital input / output channel 2 |             |
| 5                            | DIO_3         | Digital input / output channel 3 |             |
| 6                            | DIO_4         | Digital input / output channel 4 |             |
| 7                            | DIO_5         | Digital input / output channel 5 |             |
| 8                            | DIO_6         | Digital input / output channel 6 |             |
| 9                            | DIO_7         | Digital input / output channel 7 |             |
| 10                           | GND           | Ground                           |             |
| <b>Connector Type</b>        |               |                                  |             |
| B2W, 1x10-pin, 1.25 mm pitch |               |                                  |             |
| <b>Mating Connector</b>      |               |                                  |             |
| Vendor                       | PINREX        |                                  |             |
| Housing Model No.            | 712-75-10W001 |                                  |             |
| Terminal Model No.           | 712-70-T00001 |                                  |             |

### 7.13. M.2 Key B 3042 Slot (M2B1)

The 3.5"-SBC-WLU supports M.2 modules in format 3042 with Key B. The M.2 specification supports PCIe x1, USB 2.0 and USB 3.2 signals as well as UIM signals connected to Micro SIM card holder CN9. The slot can be used to integrate WWAN communication to the mainboard.

Figure 24: M.2 Key B 2042 Slot M2B1




Table 31: Pin Assignment M2B1

| Pin | Signal   | Description                        | Note |
|-----|----------|------------------------------------|------|
| 1   | -        |                                    |      |
| 2   | +3.3V    | 3.3 V power supply                 |      |
| 3   | GND      | Ground                             |      |
| 4   | +3.3V    | 3.3 V power supply                 |      |
| 5   | GND      | Ground                             |      |
| 6   | PWROFF#  | M.2 module power enable            |      |
| 7   | USB-D+   | USB 2.0 data differential pair (+) |      |
| 8   | DISABLE# | Wireless disable                   |      |
| 9   | USB-D-   | USB 2.0 data differential pair (-) |      |
| 10  | LED#     | Device active signal               |      |
| 11  | GND      | Ground                             |      |
| 12  | KEY      |                                    |      |
| 13  | KEY      |                                    |      |
| 14  | KEY      |                                    |      |
| 15  | KEY      |                                    |      |
| 16  | KEY      |                                    |      |
| 17  | KEY      |                                    |      |
| 18  | KEY      |                                    |      |
| 19  | KEY      |                                    |      |
| 20  | -        |                                    |      |
| 21  | -        |                                    |      |
| 22  | -        |                                    |      |
| 23  | -        |                                    |      |

| Pin | Signal     | Description                               | Note |
|-----|------------|-------------------------------------------|------|
| 24  | -          |                                           |      |
| 25  | -          |                                           |      |
| 26  | -          |                                           |      |
| 27  | GND        | Ground                                    |      |
| 28  | -          |                                           |      |
| 29  | USB3.0_RX- | USB 3.2 receiver differential pair (-)    |      |
| 30  | UIM_RESET* | SIM card reset                            |      |
| 31  | USB3.0_RX+ | USB 3.2 receiver differential pair (+)    |      |
| 32  | UIM_CLK*   | SIM card clock                            |      |
| 33  | GND        | Ground                                    |      |
| 34  | UIM_DATA*  | SIM card data                             |      |
| 35  | USB3.0_TX- | USB 3.2 transmitter differential pair (-) |      |
| 36  | UIM_PWR*   | SIM card power                            |      |
| 37  | USB3.0_TX+ | USB 3.2 transmitter differential pair (+) |      |
| 38  | -          |                                           |      |
| 39  | GND        | Ground                                    |      |
| 40  | -          |                                           |      |
| 41  | PERn0      | PCIe Lane 0 receiver pair (-)             |      |
| 42  | -          |                                           |      |
| 43  | PERp0      | PCIe Lane 0 receiver pair (+)             |      |
| 44  | -          |                                           |      |
| 45  | GND        | Ground                                    |      |
| 46  | -          |                                           |      |
| 47  | PETn0      | PCIe Lane 0 transmitter pair (-)          |      |
| 48  | -          |                                           |      |
| 49  | PETp0      | PCIe Lane 0 transmitter pair (+)          |      |
| 50  | PERST#     | PCIe reset                                |      |
| 51  | GND        | Ground                                    |      |
| 52  | CLKREQ#    | Reference clock request signal            |      |
| 53  | REFCLKn    | PCIe reference clock pair (-)             |      |
| 54  | WAKE#      | PCIe wake                                 |      |
| 55  | REFCLKp    | PCIe reference clock pair (+)             |      |
| 56  | -          |                                           |      |
| 57  | GND        | Ground                                    |      |
| 58  | -          |                                           |      |
| 59  | -          |                                           |      |
| 60  | -          |                                           |      |
| 61  | -          |                                           |      |
| 62  | -          |                                           |      |
| 63  | -          |                                           |      |
| 64  | -          |                                           |      |
| 65  | -          |                                           |      |

| Pin | Signal     | Description                   | Note |
|-----|------------|-------------------------------|------|
| 66  | SIM_DETECT | SIM card detect               |      |
| 67  | -          |                               |      |
| 68  | SUSCLK     | 32.768 kHz clock supply input |      |
| 69  | -          |                               |      |
| 70  | +3.3V      | 3.3 V power supply            |      |
| 71  | GND        | Ground                        |      |
| 72  | +3.3V      | 3.3 V power supply            |      |
| 73  | GND        | Ground                        |      |
| 74  | +3.3V      | 3.3 V power supply            |      |
| 75  | -          |                               |      |




---

\* These pins are connected to CN9 Micro SIM card holder directly.

---

## 7.14. M.2 Key E 2230 Slot (M2E1)

The 3.5"-SBC-WLU supports M.2 modules in format 2230 with Key E. The M.2 specification supports PCIe x1, USB 2.0 and / or CNVi signals. The slot can be used to integrate WLAN (Wi-Fi or CNVi Wi-Fi) and / or Bluetooth communication to the mainboard.

Figure 25: M.2 Key E 2230 Slot M2E1




Table 32: Pin Assignment M2E1

| Pin | Key E*     |                             | CNVi*    |                          | Note |
|-----|------------|-----------------------------|----------|--------------------------|------|
|     | Signal     | Description                 | Signal   | Description              |      |
| 1   | GND        | Ground                      | GND      | Ground                   |      |
| 2   | +3.3V      | 3.3 V power supply          | +3.3V    | 3.3 V power supply       |      |
| 3   | USB_D+     | USB 2.0 data diff. pair (+) | -        |                          |      |
| 4   | +3.3V      | 3.3 V power supply          | +3.3V    | 3.3 V power supply       |      |
| 5   | USB_D-     | USB 2.0 data diff. pair (-) | -        |                          |      |
| 6   | LED1#      | Device active signal 1      | LED1#    | Device active signal 1   |      |
| 7   | GND        | Ground                      | GND      | Ground                   |      |
| 8   | PCM_CLK    | PCM synchronous data clock  | -        |                          |      |
| 9   | -          |                             | WGR_D1N  | CNVio bus Rx Lane 1 (-)  |      |
| 10  | PCM_SYNC   | PCM synchronous data sync   | LCP_RSTN | RF companion (CRF) reset |      |
| 11  | -          |                             | WGR_D1P  | CNVio bus Rx Lane 1 (+)  |      |
| 12  | PCM_IN     | PCM synchronous data input  | -        |                          |      |
| 13  | GND        | Ground                      | GND      | Ground                   |      |
| 14  | PCM_OUT    | PCM synchronous data output | CLKREQ0  | Clock request            |      |
| 15  | -          |                             | WGR_D0N  | CNVio bus Rx Lane 0 (-)  |      |
| 16  | LED2#      | Device active signal 2      | LED2#    | Device active signal 2   |      |
| 17  | -          |                             | WGR_D0P  | CNVio bus Rx Lane 0 (+)  |      |
| 18  | GND        | Ground                      | GND      | Ground                   |      |
| 19  | GND        | Ground                      | GND      | Ground                   |      |
| 20  | UART_WAKE# | UART wake-up                | -        |                          |      |
| 21  | -          |                             | WGR_CLKN | CNVio bus Rx clock (-)   |      |
| 22  | UART_RX    | UART data input             | BRI_RSP  | BRI bus Rx               |      |
| 23  | -          |                             | WGR_CLKP | CNVio bus Rx clock (+)   |      |

| Pin | Key E*      |                                | CNVi*       |                               | Note |
|-----|-------------|--------------------------------|-------------|-------------------------------|------|
|     | Signal      | Description                    | Signal      | Description                   |      |
| 24  | Key         |                                | Key         |                               |      |
| 25  | Key         |                                | Key         |                               |      |
| 26  | Key         |                                | Key         |                               |      |
| 27  | Key         |                                | Key         |                               |      |
| 28  | Key         |                                | Key         |                               |      |
| 29  | Key         |                                | Key         |                               |      |
| 30  | Key         |                                | Key         |                               |      |
| 31  | Key         |                                | Key         |                               |      |
| 32  | UART_TX     | UART data output               | RGI_DT      | RGI bus Tx                    |      |
| 33  | GND         | Ground                         | GND         | Ground                        |      |
| 34  | UART_CTS    | UART clear to send             | RGI_RSP     | RGI bus Rx                    |      |
| 35  | PET0+       | PCIe Lane 0 Tx pair (+)        | -           |                               |      |
| 36  | UART_RTS    | UART request to send           | BRI_DT      | BRI bus Tx                    |      |
| 37  | PET0-       | PCIe Lane 0 Tx pair (-)        | -           |                               |      |
| 38  | Clink_RST   | Wi-Fi CLINK host bus reset     | -           |                               |      |
| 39  | GND         | Ground                         | GND         | Ground                        |      |
| 40  | Clink_DATA  | Wi-Fi CLINK host bus data      | -           |                               |      |
| 41  | PER0+       | PCIe Lane 0 Rx pair (+)        | -           |                               |      |
| 42  | Clink_CLK   | Wi-Fi CLINK host bus clock     | -           |                               |      |
| 43  | PER0-       | PCIe Lane 0 Rx pair (-)        | -           |                               |      |
| 44  | -           |                                | -           |                               |      |
| 45  | GND         | Ground                         | GND         | Ground                        |      |
| 46  | -           |                                | -           |                               |      |
| 47  | REFCLK0+    | PCIe reference clock pair (+)  | -           |                               |      |
| 48  | -           |                                | -           |                               |      |
| 49  | REFCLK0-    | PCIe reference clock pair (-)  | -           |                               |      |
| 50  | SUSCLK      | 32.768 kHz clock supply input  | SUSCLK      | 32.768 kHz clock supply input |      |
| 51  | GND         | Ground                         | GND         | Ground                        |      |
| 52  | PERST0#     | PCIe reset                     | -           |                               |      |
| 53  | CLKREQ0#    | Reference clock request signal | -           |                               |      |
| 54  | W_DISABLE2# | Wireless disable 2             | W_DISABLE2# | Wireless disable 2            |      |
| 55  | PEWAKE0#    | PCIe wake                      | -           |                               |      |
| 56  | W_DISABLE1# | Wireless disable 1             | W_DISABLE1# | Wireless disable 1            |      |
| 57  | GND         | Ground                         | GND         | Ground                        |      |
| 58  | -           |                                | -           |                               |      |
| 59  | -           |                                | WT_D1N      | CNVio bus Tx Lane 1 (-)       |      |
| 60  | -           |                                | -           |                               |      |
| 61  | -           |                                | WT_D1P      | CNVio bus Tx Lane 1 (+)       |      |
| 62  | -           |                                | -           |                               |      |
| 63  | GND         | Ground                         | GND         | Ground                        |      |
| 64  | -           |                                | REFCLK0     | Reference clock               |      |

| Pin | Key E* |                    | CNVi*   |                         | Note |
|-----|--------|--------------------|---------|-------------------------|------|
|     | Signal | Description        | Signal  | Description             |      |
| 65  | -      |                    | WT_D0N  | CNVio bus Tx Lane 0 (-) |      |
| 66  | -      |                    | -       |                         |      |
| 67  | -      |                    | WT_D0P  | CNVio bus Tx Lane 0 (+) |      |
| 68  | -      |                    | -       |                         |      |
| 69  | GND    | Ground             | GND     | Ground                  |      |
| 70  | -      |                    | -       |                         |      |
| 71  | -      |                    | WT_CLKN | CNVio bus Tx clock (-)  |      |
| 72  | +3.3V  | 3.3 V power supply | +3.3V   | 3.3 V power supply      |      |
| 73  | -      |                    | WT_CLKP | CNVio bus Tx clock (+)  |      |
| 74  | +3.3V  | 3.3 V power supply | +3.3V   | 3.3 V power supply      |      |
| 75  | GND    | Ground             | GND     | Ground                  |      |




---

\* Integrated CNVi can be selected by the jumper JP4.

---

## 7.15. M.2 Key M 2242 / 2280 Slot (M2M1)

The 3.5"-SBC-WLU supports M.2 modules in format 2242 or 2280 with Key M. The M.2 specification supports PCIe x4 and SATA 3.0 signals. The slot can be used to integrate an M.2 PCIe x4 SSD (NVMe) or M.2 SATA SSD to the mainboard.

Figure 26: M.2 Key M 2242 / 2280 Slot M2M1




Table 33: Pin Assignment M2M1

| Pin | Signal             | Description                                            | Note |
|-----|--------------------|--------------------------------------------------------|------|
| 1   | GND                | Ground                                                 |      |
| 2   | +3.3V              | 3.3 V power supply                                     |      |
| 3   | GND                | Ground                                                 |      |
| 4   | +3.3V              | 3.3 V power supply                                     |      |
| 5   | PERn3              | PCIe Lane 3 receiver pair (-)                          |      |
| 6   | -                  |                                                        |      |
| 7   | PERp3              | PCIe Lane 3 receiver pair (+)                          |      |
| 8   | -                  | -                                                      |      |
| 9   | GND                | Ground                                                 |      |
| 10  | DAS / DSS# / LED1# | Device active signal / disable staggered spin-up / LED |      |
| 11  | PETn3              | PCIe Lane 3 transmitter pair (-)                       |      |
| 12  | +3.3V              | 3.3 V power supply                                     |      |
| 13  | PETp3              | PCIe Lane 3 transmitter pair (+)                       |      |
| 14  | +3.3V              | 3.3 V power supply                                     |      |
| 15  | GND                | Ground                                                 |      |
| 16  | +3.3V              | 3.3 V power supply                                     |      |
| 17  | PERn2              | PCIe Lane 2 receiver pair (-)                          |      |
| 18  | +3.3V              | 3.3 V power supply                                     |      |
| 19  | PERp2              | PCIe Lane 2 receiver pair (-)                          |      |
| 20  | -                  |                                                        |      |
| 21  | GND                | Ground                                                 |      |
| 22  | -                  |                                                        |      |
| 23  | PETn2              | PCIe Lane 2 transmitter pair (-)                       |      |
| 24  | -                  |                                                        |      |
| 25  | PETp2              | PCIe Lane 2 transmitter pair (+)                       |      |
| 26  | -                  |                                                        |      |

| Pin | Signal          | Description                                                  | Note |
|-----|-----------------|--------------------------------------------------------------|------|
| 27  | GND             | Ground                                                       |      |
| 28  | -               |                                                              |      |
| 29  | PERn1           | PCIe Lane 1 receiver pair (-)                                |      |
| 30  | -               |                                                              |      |
| 31  | PERp1           | PCIe Lane 1 receiver pair (+)                                |      |
| 32  | -               |                                                              |      |
| 33  | GND             | Ground                                                       |      |
| 34  | -               |                                                              |      |
| 35  | PETn1           | PCIe Lane 1 transmitter pair (-)                             |      |
| 36  | -               |                                                              |      |
| 37  | PETp1           | PCIe Lane 1 transmitter pair (+)                             |      |
| 38  | DEVSLP          | Device sleep                                                 |      |
| 39  | GND             | Ground                                                       |      |
| 40  | -               |                                                              |      |
| 41  | PERn0 / SATA_B+ | PCIe Lane 0 receiver pair (-) / SATA receiver pair (+)       |      |
| 42  | -               |                                                              |      |
| 43  | PERp0 / SATA_B- | PCIe Lane 0 receiver pair (+) / SATA receiver pair (-)       |      |
| 44  | -               |                                                              |      |
| 45  | GND             | Ground                                                       |      |
| 46  | -               |                                                              |      |
| 47  | PETn0 / SATA_A- | PCIe Lane 0 transmitter pair (-) / SATA transmitter pair (-) |      |
| 48  | -               |                                                              |      |
| 49  | PETp0 / SATA_A+ | PCIe Lane 0 transmitter pair (+) / SATA transmitter pair (+) |      |
| 50  | PERST# / -      | PCIe reset                                                   |      |
| 51  | GND             | Ground                                                       |      |
| 52  | CLKREQ# / -     | Reference clock request signal                               |      |
| 53  | REFCLKn         | PCIe reference clock pair (-)                                |      |
| 54  | PEWAKE# / -     | PCIe wake                                                    |      |
| 55  | REFCLKp         | PCIe reference clock pair (+)                                |      |
| 56  | -               |                                                              |      |
| 57  | GND             | Ground                                                       |      |
| 58  | -               |                                                              |      |
| 59  | Key             |                                                              |      |
| 60  | Key             |                                                              |      |
| 61  | Key             |                                                              |      |
| 62  | Key             |                                                              |      |
| 63  | Key             |                                                              |      |
| 64  | Key             |                                                              |      |
| 65  | Key             |                                                              |      |
| 66  | Key             |                                                              |      |
| 67  | -               |                                                              |      |
| 68  | SUSCLK          | 32.768 kHz clock supply input                                |      |

| Pin | Signal | Description        | Note |
|-----|--------|--------------------|------|
| 69  | PEDET  | PCIe detect        |      |
| 70  | +3.3V  | 3.3 V power supply |      |
| 71  | GND    | Ground             |      |
| 72  | +3.3V  | 3.3 V power supply |      |
| 73  | GND    | Ground             |      |
| 74  | +3.3V  | 3.3 V power supply |      |
| 75  | GND    | Ground             |      |

## 7.16. Micro SIM Card Holder for M.2 Key B (CN9)

The Micro SIM card holder CN9 is intended to accommodate an Micro SIM card and connected to UIM signals on the M.2 Key B slot.

Figure 27: Micro SIM Card Holder CN9




Table 34: Pin Assignment CN9

| Pin | Signal | Description                     | Note |
|-----|--------|---------------------------------|------|
| C1  | VCC    | Power +3.3 V                    |      |
| C2  | GND    | Ground                          |      |
| C3  | RST    | Reset signal                    |      |
| C4  | VPP    | Programming voltage input       |      |
| C5  | CLK    | Clock signal                    |      |
| C6  | IO     | Input or Output for serial data |      |

## 7.17. M.2 Key B / M.2 Key E Activity Indicator Header (CN1 & CN4)

The header CN1 is intended to connect M.2 Key B activity LED cable.

The pin header CN4 is intended to connect M.2 Key E activity LED cable.

Figure 28: M.2 Key B Activity Indicator Header CN1




Table 35: Pin Assignment CN1

| Pin                        | Signal | Description | Note |
|----------------------------|--------|-------------|------|
| 1                          | LED+   |             |      |
| 2                          | LED-   |             |      |
| <b>Connector Type</b>      |        |             |      |
| B2W, 1x2-pin, 2.0 mm pitch |        |             |      |

Figure 29: M.2 Key E Activity Indicator Header CN4





Table 36: Pin Assignment CN4

| Pin                        | Signal     | Description | Note |
|----------------------------|------------|-------------|------|
| 1                          | WLAN_LED1+ |             |      |
| 2                          | WLAN_LED1- |             |      |
| 3                          | BR_LED2+   |             |      |
| 4                          | BR_LED2-   |             |      |
| <b>Connector Type</b>      |            |             |      |
| B2W, 1x4-pin, 2.0 mm pitch |            |             |      |

### 7.18. Switches and Jumpers

The product has several jumpers which must be properly configured to ensure correct operation.

Figure 30: Jumper Connector



For a three-pin jumper (see Figure 29), the jumper setting is designated "1-2" when the jumper connects pins 1 and 2. The jumper setting is designated "2-3" when pins 2 and 3 are connected and so on. You will see that one of the lines surrounding a jumper pin is thick, which indicates pin No.1.

To move a jumper from one position to another, use needle-nose pliers or tweezers to pull the pin cap off the pins and move it to the desired position.

#### 7.18.1. LVDS Panel Power Selection (JP1)

The 2.54 mm pitch "LVDS Panel Power Selection" jumper (JP1) can be used to select LVDS panel and backlight power voltage.

Figure 31: LVDS Panel Power Selection JP1




Table 37: Pin Assignment JP1

| Jumper 1 Position |         | Description             |
|-------------------|---------|-------------------------|
| Pin 1-3           | Pin 3-5 |                         |
| X                 | -       | Backlight Power = +12 V |
| -                 | X       | Backlight Power = +5 V  |
| Jumper 2 Position |         | Description             |
| Pin 2-4           | Pin 4-6 |                         |
| X                 | -       | Panel Power = +3.3 V    |
| -                 | X       | Panel Power = +5 V      |

"X" = Jumper set (short) and "-" = jumper not set (open)

### 7.18.2. LVDS Backlight Control Selection (JP2)

The 2.0 mm pitch "LVDS Backlight Control Selection" jumper (JP2) can be used to select by which mode the brightness level in the LCD panel is controlled.

Figure 32: LVDS Backlight Control Selection JP2



Table 38: Pin Assignment JP2

| Jumper 1 Position |         | Description          |
|-------------------|---------|----------------------|
| Pin 1-2           | Pin 2-3 |                      |
| X                 | -       | PWM Control Mode     |
| -                 | X       | Voltage Control Mode |

"X" = Jumper set (short) and "-" = jumper not set (open)

### 7.18.3. LVDS Backlight Enable Selection (JP3)

The 2.0 mm patch "LVDS Backlight Enable Selection" jumper (JP3) can be used to select voltage level of backlight enable signal.

Figure 33: LVDS Backlight Enable Selection JP3




Table 39: Pin Assignment JP3

| Jumper 1 Position |         | Description                     |
|-------------------|---------|---------------------------------|
| Pin 1-3           | Pin 3-5 |                                 |
| X                 | -       | Backlight Enable Level = +3.3 V |
| -                 | X       | Backlight Enable Level = +5 V   |
| Jumper 2 Position |         | Description                     |
| Pin 2-4           | Pin 4-6 |                                 |
| X                 | -       | Backlight Enable High Active    |
| -                 | X       | Backlight Enable Low Active     |

"X" = Jumper set (short) and "-" = jumper not set (open)

#### 7.18.4. Integrated CNVi Selection for M2E1 (JP4)

The 2.0 mm pitch "Integrated CNVi Selection for M2E1" jumper (JP4) can be used to select whether or not to enable CNVi device in M.2 Key E slot.

Figure 34: Integrated CNVi Selection JP4



Table 40: Pin Assignment JP4

| Jumper 1 Position |         | Description              |
|-------------------|---------|--------------------------|
| Pin 1-2           | Pin 2-3 |                          |
| X                 | -       | Integrated CNVi Disabled |
| -                 | X       | Integrated CNVi Enabled  |

"X" = Jumper set (short) and "-" = jumper not set (open)

#### 7.18.5. Flash Descriptor Security Override Selection (JP5)

The 2.0 mm pitch "Flash Descriptor Security Override Selection" jumper (JP5) can be used to specify whether to override the flash descriptor.

Figure 35: Flash Descriptor Security Override Selection JP5



Table 41: Pin Assignment JP5

| Jumper 1 Position |         | Description             |
|-------------------|---------|-------------------------|
| Pin 1-2           | Pin 2-3 |                         |
| X                 | -       | Normal Operation        |
| -                 | X       | Flash Security Override |

"X" = Jumper set (short) and "-" = jumper not set (open)

#### 7.18.6. AT / ATX Power Mode Selection (JP6)

The 2.0 mm pitch jumper JP6 can be used to select AT power mode or ATX power mode.

Figure 36: AT / ATX Power Mode Selection JP6




Table 42: Pin Assignment JP6

| Jumper 1 Position |         | Description |
|-------------------|---------|-------------|
| Pin 1-2           | Pin 2-3 |             |
| X                 | -       | ATX Mode    |
| -                 | X       | AT Mode     |

"X" = Jumper set (short) and "-" = jumper not set (open)

### 7.18.7. Clear CMOS Selection (JP7)

The 2.0 mm pitch "Clear COMS Selection" jumper (JP7) can be used to reset the Real Time Clock (RTC) and drain RTC well.

The jumper has one position: Pin 1-2 mounted (default position) and Pin 2-3 mounted. More information on setting the "Clear CMOS Selection" jumper can be found in the following table.

Figure 37: Clear CMOS Selection JP7



Table 43: Pin Assignment JP7

| Jumper 1 Position |         | Description                                                       |
|-------------------|---------|-------------------------------------------------------------------|
| Pin 1-2           | Pin 2-3 |                                                                   |
| X                 | -       | Normal Operation (default position)                               |
| -                 | X       | Clear CMOS (board does not boot with the jumper in this position) |

"X" = Jumper set (short) and "-" = jumper not set (open)



Do not leave the jumper in position 2-3, otherwise if the power is disconnected, the battery will fully deplete within a few weeks.

### 7.18.8. USB Power Selection (JP9)

The 2.0 mm pitch "USB Power Selection" jumper (JP9) can be used to determine whether the USB ports are powered in the S4 / S5 state.

Figure 38: USB Power Selection JP9




Table 44: Pin Assignment JP9

| Jumper 1 Position |         | Description |
|-------------------|---------|-------------|
| Pin 1-2           | Pin 2-3 |             |
| X                 | -       | +5 V        |
| -                 | X       | +5 VSB      |

“X” = Jumper set (short) and “-” = jumper not set (open)

### 7.18.9. MFG Mode Selection (JP10)

The 2.0 mm pitch "MFG Mode Selection" jumper (JP10) can be used to rewrite Intel ME firmware onto another version.

Figure 39: MFG Mode Selection JP10




Table 45: Pin Assignment JP10

| Jumper 1 Position |         | Description      |
|-------------------|---------|------------------|
| Pin 1-2           | Pin 2-3 |                  |
| X                 | -       | Normal Operation |
| -                 | X       | Enable MFG Mode  |

“X” = Jumper set (short) and “-” = jumper not set (open)

## 8/ BIOS

### 8.1. Starting the uEFI BIOS

The 3.5"-SBC-WLU is provided with a Kontron-customized, pre-installed and configured version of AMI Aptio® V uEFI BIOS. AMI BIOS firmware is based on the Unified Extensible Firmware Interface (UEFI) specification and the Intel® Platform Innovation Framework for EFI. This uEFI BIOS provides a variety of new and enhanced functions specifically tailored to the hardware features of the 3.5"-SBC-WLU.

The uEFI BIOS comes with a setup program that provides quick and easy access to the individual function settings for control or modification of the uEFI BIOS configuration. The setup program allows the accessing of various menus that provide functions or access to sub-menus with more specific functions of their own.

To start the uEFI BIOS setup program, follow the steps below:

1. Power on the board.
2. Wait until the first characters appear on the screen (POST messages or splash screen).
3. Press the <DEL> key.
4. If the uEFI BIOS is password-protected, a request for password will appear. Enter either the User Password or the Supervisor Password (see Security menu), press <RETURN>, and proceed with step 5.
5. A setup menu will appear.

The 3.5"-SBC-WLU uEFI BIOS setup program uses a hot key-based navigation system. A hot key legend bar is located on the bottom of the setup screens.

The following table provides information concerning the usage of these hot keys.

**Table 46: Hotkeys Table**

| Signal     | Description                                                                                                                                        |
|------------|----------------------------------------------------------------------------------------------------------------------------------------------------|
| <F1>       | The <F1> key invokes the General Help window.                                                                                                      |
| <->        | The <Minus> key selects the next lower value within a field.                                                                                       |
| <+>        | The <Plus> key selects the next higher value within a field.                                                                                       |
| <F2>       | The <F2> key loads the previous values.                                                                                                            |
| <F3>       | The <F3> key loads the standard default values.                                                                                                    |
| <F4>       | The <F4> key saves the current settings and exit the uEFI BIOS setup.                                                                              |
| <→> or <←> | The <Left/Right> arrows selects major setup menus on the menu bar. For example: Main, Advanced, Security, etc.                                     |
| <↑> or <↓> | The <Up/Down> arrows selects fields in the current menu. For example: A setup function or a sub-screen.                                            |
| <ESC>      | The <ESC> key exits a major setup menu and enter the Exit setup menu.<br>Pressing the <ESC> key in a sub-menu displays the next higher menu level. |
| <RETURN>   | The <RETURN> key executes a command or select a submenu.                                                                                           |

## 8.2. Starting the uEFI BIOS

The Setup utility features shows six menus in the selection bar at the top of the screen:

- ▶ Main
- ▶ Advanced
- ▶ Power
- ▶ Boot
- ▶ Security
- ▶ Save & Exit

The Setup menus are selected via the left and right arrow keys. The currently active menu and the currently active uEFI BIOS Setup item are highlighted in white. Each Setup menu provides two main frames. The left frame displays all available functions. Functions that can be configured are displayed in blue. Functions displayed in gray provide information about the status or the operational configuration. The right frame displays an Item Specific Help window providing an explanation of the respective function.

### 8.2.1. Main Setup Menu

Upon entering the uEFI BIOS Setup program, the Main Setup menu is displayed. This screen lists the Main Setup menu sub-screens and provides basic system information. Additionally functions for setting the system time and date are offered.

**Table 47: Main Setup Menu Sub-Screens and Functions**

| Function             | Description                                                                         |
|----------------------|-------------------------------------------------------------------------------------|
| BIOS Information     | Read only field.<br>Displays information about the system BIOS                      |
| Memory Information   | Read only field.<br>Displays information about total memory                         |
| ME Information       | Read only field.<br>Displays information about Intel Management Engine (ME) version |
| Firmware Information | Code version and firmware information                                               |
| System Date          | Set System Date                                                                     |
| System Time          | Set System Time                                                                     |

Figure 40: BIOS Main Menu Screen System Data and Time

| BIOS SETUP UTILITY                                               |              |                                      |      |                                                                                                                                                                                                                                                                 |             |
|------------------------------------------------------------------|--------------|--------------------------------------|------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------|
| Main                                                             | Advanc<br>ed | Power                                | Boot | Security                                                                                                                                                                                                                                                        | Save & Exit |
| Product Information                                              |              |                                      |      | <div>→ ←: Select Screen</div> <div>↑ ↓: Select Item</div> <div>Enter: Select</div> <div>+/-: Change Opt.</div> <div>F1: General Help</div> <div>F2: Previous Values</div> <div>F3: Optimized Defaults</div> <div>F4: Save &amp; Exit</div> <div>ESC: Exit</div> |             |
| Product Name                                                     |              | 3.5-SBC-WLU                          |      |                                                                                                                                                                                                                                                                 |             |
| BIOS Version                                                     |              | WHLUVEX.001 (x64)                    |      |                                                                                                                                                                                                                                                                 |             |
| BIOS Build Date                                                  |              | 01/08/2020                           |      |                                                                                                                                                                                                                                                                 |             |
| ME Firmware SKU                                                  |              | Corporate SKU                        |      |                                                                                                                                                                                                                                                                 |             |
| ME Firmware Version                                              |              | 12.0.49.1534                         |      |                                                                                                                                                                                                                                                                 |             |
| CPU Information                                                  |              |                                      |      |                                                                                                                                                                                                                                                                 |             |
| Intel® Core™ Processor i5-8365UE CPU @ 1.60 GHz                  |              |                                      |      |                                                                                                                                                                                                                                                                 |             |
| Microcode Revision                                               |              | CA                                   |      |                                                                                                                                                                                                                                                                 |             |
| Processor Cores                                                  |              | 4 Core(s) / 8 Thread(s)              |      |                                                                                                                                                                                                                                                                 |             |
| Memory Information                                               |              |                                      |      |                                                                                                                                                                                                                                                                 |             |
| Total Size                                                       |              | 4096 MB (DDR4)                       |      |                                                                                                                                                                                                                                                                 |             |
| Frequency                                                        |              | 2400 MHz                             |      |                                                                                                                                                                                                                                                                 |             |
| Board Information                                                |              |                                      |      |                                                                                                                                                                                                                                                                 |             |
| UUID                                                             |              | 01F94600-FF9E-13E0-8001-0050080CB60F |      |                                                                                                                                                                                                                                                                 |             |
| Serial #                                                         |              | BU9C129C0010                         |      |                                                                                                                                                                                                                                                                 |             |
| LAN1 MAC Address                                                 |              | 00:50:08:0C:B6:0F                    |      |                                                                                                                                                                                                                                                                 |             |
| LAN2 MAC Address                                                 |              | 00:50:08:0C:B6:10                    |      |                                                                                                                                                                                                                                                                 |             |
| System Date                                                      |              | [Wed 02/26/2020]                     |      |                                                                                                                                                                                                                                                                 |             |
| System Time                                                      |              | [15:54:55]                           |      |                                                                                                                                                                                                                                                                 |             |
| Access Level                                                     |              | Administrator                        |      |                                                                                                                                                                                                                                                                 |             |
| Version 2.20.1275. Copyright (C) 2020, American Megatrends, Inc. |              |                                      |      |                                                                                                                                                                                                                                                                 |             |

| Feature     | Option       | Description                                            |
|-------------|--------------|--------------------------------------------------------|
| System Date | [dd/mm/yyyy] | Set the Date. Use Tab to switch between Data elements. |
| System Time | [hh:mm:ss]   | Set the Time. Use Tab to switch between Time elements. |

## 8.2.2. Advanced Setup Menu

The Advanced setup menu provides sub-screens and functions for advanced configurations. The following sub-screen functions are included in the menu:

- ▶ LAN & Audio Configuration
- ▶ Display Configuration
- ▶ Super IO Configuration
- ▶ CPU Chipset Configuration
- ▶ NVMe Configuration
- ▶ SATA Configuration
- ▶ USB Configuration
- ▶ AMT Configuration
- ▶ Trusted Computing
- ▶ H/W Monitor
- ▶ Network Stack Configuration

---

**NOTICE**

Setting items on this screen to incorrect values may cause the system to malfunction.

---

Figure 41: BIOS Advanced Menu

| BIOS SETUP UTILITY                                               |          |            |      |                                                                                                                                                                                  |             |
|------------------------------------------------------------------|----------|------------|------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------|
| Main                                                             | Advanced | Power      | Boot | Security                                                                                                                                                                         | Save & Exit |
| Onboard LAN1 Controller                                          |          | [Enabled]  |      |                                                                                                                                                                                  |             |
| Onboard LAN2 Controller                                          |          | [Enabled]  |      |                                                                                                                                                                                  |             |
| Load I219 UNDI Driver                                            |          | [Disabled] |      |                                                                                                                                                                                  |             |
| Load I210 UNDI Driver                                            |          | [Disabled] |      |                                                                                                                                                                                  |             |
| Audio Controller                                                 |          | [Enabled]  |      |                                                                                                                                                                                  |             |
| > Display Configuration                                          |          |            |      | → ←: Select Screen<br>↑ ↓: Select Item<br>Enter: Select<br>+/-: Change Opt.<br>F1: General Help<br>F2: Previous Values<br>F3: Optimized Defaults<br>F4: Save & Exit<br>ESC: Exit |             |
| > Super IO Configuration                                         |          |            |      |                                                                                                                                                                                  |             |
| > CPU Chipset Configuration                                      |          |            |      |                                                                                                                                                                                  |             |
| > NVMe Configuration                                             |          |            |      |                                                                                                                                                                                  |             |
| > SATA Configuration                                             |          |            |      |                                                                                                                                                                                  |             |
| > USB Configuration                                              |          |            |      |                                                                                                                                                                                  |             |
| > AMT Configuration                                              |          |            |      |                                                                                                                                                                                  |             |
| > Trusted Computing                                              |          |            |      |                                                                                                                                                                                  |             |
| > H/W Monitor                                                    |          |            |      |                                                                                                                                                                                  |             |
| > Network Stack Configuration                                    |          |            |      |                                                                                                                                                                                  |             |
| Version 2.20.1275. Copyright (C) 2020, American Megatrends, Inc. |          |            |      |                                                                                                                                                                                  |             |

| Feature                 | Option                | Description                                                              |
|-------------------------|-----------------------|--------------------------------------------------------------------------|
| Onboard LAN1 Controller | [Disabled], [Enabled] | Select whether to enable or disable Onboard LAN1 Controller. Intel-i219. |
| Onboard LAN2 Controller | [Disabled], [Enabled] | Select whether to enable or disable Onboard LAN2 Controller. Intel-i210. |
| Load I219 UNDI Driver   | [Disabled], [Enabled] | Select whether to load LAN UNDI Driver.                                  |
| Load I210 UNDI Driver   | [Disabled], [Enabled] | Select whether to load LAN UNDI Driver.                                  |
| Audio Controller        | [Disabled], [Enabled] | Select whether to enable or disable Audio Controller.                    |

Figure 42: BIOS Advanced Menu - Display Configuration

| BIOS SETUP UTILITY                                               |          |                |                        |          |             |
|------------------------------------------------------------------|----------|----------------|------------------------|----------|-------------|
| Main                                                             | Advanced | Power          | Boot                   | Security | Save & Exit |
| Display Configuration                                            |          |                |                        |          |             |
| Primary Display                                                  |          | [IGFX]         |                        |          |             |
| Internal Graphics*                                               |          | [Enabled]      |                        |          |             |
| Aperture Size                                                    |          | [256MB]        |                        |          |             |
| DVMT Pre-Allocated                                               |          | [32M]          |                        |          |             |
| DVMT Total Gfx Mem                                               |          | [256MB]        | → ←: Select Screen     |          |             |
|                                                                  |          |                | ↑ ↓: Select Item       |          |             |
| Active LVDS                                                      |          | [Enabled]      | Enter: Select          |          |             |
| LVDS Panel Type                                                  |          | [1366x768 1CH] | +/-: Change Opt.       |          |             |
| LVDS Panel Color Depth                                           |          | [18Bit]        | F1: General Help       |          |             |
| PWM Backlight Control                                            |          | [By External]  | F2: Previous Values    |          |             |
| LVDS Backlight Control Mode                                      |          | [PWM]          | F3: Optimized Defaults |          |             |
| LVDS Backlight Control - PWM**                                   |          | 127            | F4: Save & Exit        |          |             |
| LVDS Backlight Control - Voltage***                              |          | [2.5 V]        | ESC: Exit              |          |             |
| Version 2.20.1275. Copyright (C) 2020, American Megatrends, Inc. |          |                |                        |          |             |

\* This item is selectable only when selecting PEG for the Primary Display.

\*\* This item appears only when selecting PWM for the LVDS Backlight Control Mode.

\*\*\* This item appears only when selecting Voltage for the LVDS Backlight Control Mode.

| Feature            | Option                                                                                                                        | Description                                                                                                                                                                 |
|--------------------|-------------------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Primary Display    | [IGFX], [PEG]                                                                                                                 | Select which of IGFX / PEG Graphics device should be Primary Display.                                                                                                       |
| Internal Graphics  | [Disabled], [Enabled]                                                                                                         | Keep IGFX enabled based on the setup options.                                                                                                                               |
| Aperture Size      | [128MB], [256MB], [512MB], [1024MB], [2048MB]                                                                                 | Select the Aperture Size.<br>Note: Above 4GB MMIO BIOS assignment is automatically enabled when selecting 2048MB aperture. To use this feature, please disable CSM Support. |
| DVMT Pre-Allocated | [32M], [64M], [4M], [8M], [12M], [16M], [20M], [24M], [28M], [32M], [32M/F7], [36M], [40M], [44M], [48M], [52M], [56M], [60M] | Select DVMT 5.0 Pre-Allocated (Fixed) Graphics Memory size used by the Internal Graphics Device.                                                                            |
| DVMT Total Gfx Mem | [128M], [256M], [MAX]                                                                                                         | Select DVMT 5.0 Total Graphic Memory size used by the Internal Graphics Device.                                                                                             |
| Active LVDS        | [Disabled], [Enabled]                                                                                                         | Select the Active LVDS Configuration.<br>[Disabled]: VBIOS does not enable LVDS.<br>[Enabled]: VBIOS will enable LVDS.                                                      |
| LVDS Panel Type    | [800x600 1CH], [1024x768 1CH], [1280x1024 2CH],                                                                               | LVDS panel by selecting the appropriate setup item.                                                                                                                         |

| Feature                          | Option                                                                                                     | Description                                                                                                                                                        |
|----------------------------------|------------------------------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|                                  | [1366x768 1CH],<br>[1366x768 2CH],<br>[1600x1200 2CH],<br>[1920x1080 2CH]                                  |                                                                                                                                                                    |
| LVDS Panel Color Depth           | [18Bit], [24Bit]                                                                                           | LVDS panel color depth by appropriate setup item.                                                                                                                  |
| PWM Backlight Control            | [By External], [By Internal]                                                                               | CN21 LVDS Backlight Power Wafer Pin 2 output control<br>[By External]: Control by external HW circuit.<br>[By Internal]: Control by LBKL_CTL on the Intel Chipset. |
| LVDS Backlight Control Mode      | [Voltage], [PWM]                                                                                           | CN21 LVDS Backlight Power output control<br>[Voltage]: Pin 1 output<br>[PWM]: Pin 2 output                                                                         |
| LVDS Backlight Control - Voltage | [0.0 V], [0.5 V], [1.0 V],<br>[1.5 V], [2.0 V], [2.5 V],<br>[3.0 V], [3.5 V], [4.0 V],<br>[4.5 V], [5.0 V] | Min: 0.0 V<br>Max: 5.0 V                                                                                                                                           |

Figure 43: BIOS Advanced Menu - Super IO Configuration

| BIOS SETUP UTILITY                                               |          |       |      |                        |             |
|------------------------------------------------------------------|----------|-------|------|------------------------|-------------|
| Main                                                             | Advanced | Power | Boot | Security               | Save & Exit |
| Super IO Configuration                                           |          |       |      |                        |             |
| > Serial Port 1 Configuration                                    |          |       |      | → ←: Select Screen     |             |
| > Serial Port 2 Configuration                                    |          |       |      | ↑ ↓: Select Item       |             |
|                                                                  |          |       |      | Enter: Select          |             |
|                                                                  |          |       |      | +/-: Change Opt.       |             |
|                                                                  |          |       |      | F1: General Help       |             |
|                                                                  |          |       |      | F2: Previous Values    |             |
|                                                                  |          |       |      | F3: Optimized Defaults |             |
|                                                                  |          |       |      | F4: Save & Exit        |             |
|                                                                  |          |       |      | ESC: Exit              |             |
| Version 2.20.1275. Copyright (C) 2020, American Megatrends, Inc. |          |       |      |                        |             |

Figure 44: BIOS Advanced Menu - Super IO Configuration - Serial Port 1 Configuration

| BIOS SETUP UTILITY                                               |          |                 |      |                        |             |
|------------------------------------------------------------------|----------|-----------------|------|------------------------|-------------|
| Main                                                             | Advanced | Power           | Boot | Security               | Save & Exit |
| Super Port 1 Configuration                                       |          |                 |      |                        |             |
| Serial Port                                                      |          | [Enabled]       |      | → ←: Select Screen     |             |
| Device Settings                                                  |          | IO=3F8h; IRQ=4; |      | ↑ ↓ : Select Item      |             |
| Change Setting                                                   |          | [Auto]          |      | Enter: Select          |             |
| Serial Port 1 Type                                               |          | [RS232]         |      | +/-: Change Opt.       |             |
| RS485 Deplx Mode*                                                |          | [Half Duplex]   |      | F1: General Help       |             |
| RS485 Auto Flow Control*                                         |          | [Disabled]      |      | F2: Previous Values    |             |
| RS485/422 Receiver Termination**                                 |          | [Enabled]       |      | F3: Optimized Defaults |             |
|                                                                  |          |                 |      | F4: Save & Exit        |             |
|                                                                  |          |                 |      | ESC: Exit              |             |
| Version 2.20.1275. Copyright (C) 2020, American Megatrends, Inc. |          |                 |      |                        |             |

\* These items appear only when selecting RS485 for the Serial Port 1 Type.

\*\* This item appears only when selecting RS485 or RS422 for the Serial Port 1 Type.

| Feature         | Option                                                                                                                                                                         | Description                                            |
|-----------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------------------------------------------------------|
| Serial Port     | [Disabled], [Enabled]                                                                                                                                                          | Select whether to enable or disable Serial Port (COM). |
| Change Settings | [Auto], [IO=3F8h; IRQ=4;], [IO=3F8h; IRQ=3, 4, 5, 6, 7, 9, 10, 11, 12;], [IO=2F8h; IRQ=3, 4, 5, 6, 7, 9, 10, 11, 12;], [IO=3E8h; IRQ=3, 4, 5, 6, 7, 9, 10, 11, 12;], [IO=2E8h; | Select an optional setting for Super IO device.        |

| Feature                        | Option                             | Description                                                         |
|--------------------------------|------------------------------------|---------------------------------------------------------------------|
|                                | IRQ=3, 4, 5, 6, 7, 9, 10, 11, 12;] |                                                                     |
| Serial Port 1 Type             | [RS232], [RS422], [RS485]          | Select an appropriate type for Serial Port 1.                       |
| RS485 Duplex Mode              | [Half Duplex], [Full Duplex]       | Select an appropriate RS485 Duplex Mode.                            |
| RS485 Auto Flow Control        | [Disabled], [Enabled]              | Select whether to enable or disable RS485 Auto Flow Control.        |
| RS485/422 Receiver Termination | [Disabled], [Enabled]              | Select whether to enable or disable RS485/422 Receiver Termination. |

Figure 45: BIOS Advanced Menu - Super IO Configuration - Serial Port 2 Configuration

| BIOS SETUP UTILITY                                               |          |                 |      |                        |             |
|------------------------------------------------------------------|----------|-----------------|------|------------------------|-------------|
| Main                                                             | Advanced | Power           | Boot | Security               | Save & Exit |
| Super Port 2 Configuration                                       |          |                 |      |                        |             |
| Serial Port                                                      |          | [Enabled]       |      | → ←: Select Screen     |             |
| Device Settings                                                  |          | IO=2F8h; IRQ=3; |      | ↑ ↓: Select Item       |             |
| Change Setting                                                   |          | [Auto]          |      | Enter: Select          |             |
| Serial Port 2 Type                                               |          | [RS232]         |      | +/-: Change Opt.       |             |
| RS485 Duplex Mode*                                               |          | [Half Duplex]   |      | F1: General Help       |             |
| RS485 Auto Flow Control*                                         |          | [Disabled]      |      | F2: Previous Values    |             |
| RS485/422 Receiver Termination**                                 |          | [Enabled]       |      | F3: Optimized Defaults |             |
|                                                                  |          |                 |      | F4: Save & Exit        |             |
|                                                                  |          |                 |      | ESC: Exit              |             |
| Version 2.20.1275. Copyright (C) 2020, American Megatrends, Inc. |          |                 |      |                        |             |

\* These items appear only when selecting RS485 for the Serial Port 2 Type.

\*\* This item appears only when selecting RS485 or RS422 for the Serial Port 2 Type.

| Feature            | Option                                                                                                                                                                                                            | Description                                            |
|--------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------------------------------------------------------|
| Serial Port        | [Disabled], [Enabled]                                                                                                                                                                                             | Select whether to enable or disable Serial Port (COM). |
| Change Settings    | [Auto], [IO=2F8h; IRQ=3;], [IO=3F8h; IRQ=3, 4, 5, 6, 7, 9, 10, 11, 12;], [IO=2F8h; IRQ=3, 4, 5, 6, 7, 9, 10, 11, 12;], [IO=3E8h; IRQ=3, 4, 5, 6, 7, 9, 10, 11, 12;], [IO=2E8h; IRQ=3, 4, 5, 6, 7, 9, 10, 11, 12;] | Select an optional setting for Super IO device.        |
| Serial Port 2 Type | [RS232], [RS422], [RS485]                                                                                                                                                                                         | Select an appropriate type for Serial Port 2.          |
| RS485 Duplex Mode  | [Half Duplex], [Full Duplex]                                                                                                                                                                                      | Select an appropriate RS485 Duplex Mode.               |

| Feature                        | Option                | Description                                                         |
|--------------------------------|-----------------------|---------------------------------------------------------------------|
| RS485 Auto Flow Control        | [Disabled], [Enabled] | Select whether to enable or disable RS485 Auto Flow Control.        |
| RS485/422 Receiver Termination | [Disabled], [Enabled] | Select whether to enable or disable RS485/422 Receiver Termination. |

Figure 46: BIOS Advanced Menu - CPU Chipset Configuration

| BIOS SETUP UTILITY                                               |          |            |      |                        |             |
|------------------------------------------------------------------|----------|------------|------|------------------------|-------------|
| Main                                                             | Advanced | Power      | Boot | Security               | Save & Exit |
| CPU Chipset Configuration                                        |          |            |      |                        |             |
| EIST                                                             |          | [Enabled]  |      | → ←: Select Screen     |             |
| Turbo Mode                                                       |          | [Enabled]  |      | ↑ ↓: Select Item       |             |
| Hyper-Threading                                                  |          | [Enabled]  |      | Enter: Select          |             |
| VT-d                                                             |          | [Enabled]  |      | +/-: Change Opt.       |             |
| Active Processor Cores                                           |          | [All]      |      | F1: General Help       |             |
| Intel (VMX) Virtualization Technology                            |          | [Enabled]  |      | F2: Previous Values    |             |
| Intel Trusted Execution Technology                               |          | [Disabled] |      | F3: Optimized Defaults |             |
| C states                                                         |          | [Enabled]  |      | F4: Save & Exit        |             |
|                                                                  |          |            |      | ESC: Exit              |             |
| Version 2.20.1275. Copyright (C) 2020, American Megatrends, Inc. |          |            |      |                        |             |

| Feature                               | Option                | Description                                                                                                                                                                                |
|---------------------------------------|-----------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| EIST                                  | [Disabled], [Enabled] | Select whether to enable or disable Enhanced Intel SpeedStep Technology.                                                                                                                   |
| Turbo Mode                            | [Disabled], [Enabled] | Select whether to enable or disable processor Turbo Mode (requires Intel Speed Step or Intel Speed Shift to be available and enabled).                                                     |
| Hyper-Threading                       | [Disabled], [Enabled] | Select whether to enable or disable Hyper-Threading Technology.                                                                                                                            |
| VT-d                                  | [Disabled], [Enabled] | Select whether to enable or disable VT-d capability.                                                                                                                                       |
| Active Processor Cores                | [All], [1], [2], [3]  | Select number of cores to enable in each processor package.                                                                                                                                |
| Intel (VMX) Virtualization Technology | [Disabled], [Enabled] | Select whether to enable or disable Intel Virtualization Technology. When enabled, a VMM can utilize the additional hardware capabilities provided by Vanderpool Technology.               |
| Intel Trusted Execution Technology    | [Disabled], [Enabled] | Select whether to enable or disable utilization of additional hardware capabilities provided by Intel® Trusted Execution Technology.<br>Changes require a full power cycle to take effect. |
| C states                              | [Disabled], [Enabled] | Select whether to enable or disable CPU Power Management. Allows CPU to go to C states when it's not 100% utilized.                                                                        |

Figure 47: BIOS Advanced Menu - NVMe Configuration

| BIOS SETUP UTILITY                                               |          |       |      |                                                                                                                                                                                  |             |
|------------------------------------------------------------------|----------|-------|------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------|
| Main                                                             | Advanced | Power | Boot | Security                                                                                                                                                                         | Save & Exit |
| NVMe Configuration                                               |          |       |      |                                                                                                                                                                                  |             |
| No NVMe Device Found                                             |          |       |      | → ←: Select Screen<br>↑ ↓: Select Item<br>Enter: Select<br>+/-: Change Opt.<br>F1: General Help<br>F2: Previous Values<br>F3: Optimized Defaults<br>F4: Save & Exit<br>ESC: Exit |             |
| Version 2.20.1275. Copyright (C) 2020, American Megatrends, Inc. |          |       |      |                                                                                                                                                                                  |             |

Figure 48: BIOS Advanced Menu - SATA Configuration

| BIOS SETUP UTILITY                                               |          |           |      |                        |             |
|------------------------------------------------------------------|----------|-----------|------|------------------------|-------------|
| Main                                                             | Advanced | Power     | Boot | Security               | Save & Exit |
| SATA Configuration                                               |          |           |      |                        |             |
| SATA Controller(s)                                               |          | [Enabled] |      | → ←: Select Screen     |             |
| SATA Mode Selection                                              |          | [AHCI]    |      | ↑ ↓: Select Item       |             |
|                                                                  |          |           |      | Enter: Select          |             |
| Serial ATA Port 1                                                |          | Empty     |      | +/-: Change Opt.       |             |
| Port 1                                                           |          | [Enabled] |      | F1: General Help       |             |
|                                                                  |          |           |      | F2: Previous Values    |             |
|                                                                  |          |           |      | F3: Optimized Defaults |             |
|                                                                  |          |           |      | F4: Save & Exit        |             |
|                                                                  |          |           |      | ESC: Exit              |             |
| Version 2.20.1275. Copyright (C) 2020, American Megatrends, Inc. |          |           |      |                        |             |

| Feature             | Option                                                            | Description                                          |
|---------------------|-------------------------------------------------------------------|------------------------------------------------------|
| SATA Controller     | [Enabled], [Disabled]                                             | Select whether to enable or disable SATA Controller. |
| SATA Mode Selection | [AHCI], [Intel RST Premium With Intel Optane System Acceleration] | Determine how SATA controller(s) operate.            |
| Port 1              | [Disabled], [Enabled]                                             | Select whether to enable or disable SATA Port 1.     |

Figure 49: BIOS Advanced Menu - USB Configuration

| BIOS SETUP UTILITY                                               |          |            |      |                        |             |
|------------------------------------------------------------------|----------|------------|------|------------------------|-------------|
| Main                                                             | Advanced | Power      | Boot | Security               | Save & Exit |
| USB Configuration                                                |          |            |      |                        |             |
| USB Devices:                                                     |          |            |      | → ←: Select Screen     |             |
| 1 Keyboard                                                       |          |            |      | ↑ ↓: Select Item       |             |
| Legacy USB Support                                               |          | [Enabled]  |      | Enter: Select          |             |
| XHCI Hand-off                                                    |          | [Disabled] |      | +/-: Change Opt.       |             |
| USB Mass Storage Driver Support                                  |          | [Enabled]  |      | F1: General Help       |             |
|                                                                  |          |            |      | F2: Previous Values    |             |
|                                                                  |          |            |      | F3: Optimized Defaults |             |
|                                                                  |          |            |      | F4: Save & Exit        |             |
|                                                                  |          |            |      | ESC: Exit              |             |
| Version 2.20.1275. Copyright (C) 2020, American Megatrends, Inc. |          |            |      |                        |             |

| Feature                         | Option                        | Description                                                                                                                                                                          |
|---------------------------------|-------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Legacy USB Support              | [Enabled], [Disabled], [Auto] | Select whether to enable or disable Legacy USB support. AUTO option disables legacy support if no USB devices are connected.                                                         |
| XHCI Hand-off                   | [Enabled], [Disabled]         | Select whether to enable or disable XHCI Hand-off function. This is a workaround for OSes without XHCI hand-off support. The XHCI ownership change should be claimed by XHCI driver. |
| USB Mass Storage Driver Support | [Disabled], [Enabled]         | Select whether to enable or disable USB Mass Storage Driver Support.                                                                                                                 |

Figure 50: BIOS Advanced Menu - AMT Configuration

| BIOS SETUP UTILITY                                               |          |           |      |                                                                                                                                                                                  |             |
|------------------------------------------------------------------|----------|-----------|------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------|
| Main                                                             | Advanced | Power     | Boot | Security                                                                                                                                                                         | Save & Exit |
| AMT Configuration                                                |          |           |      |                                                                                                                                                                                  |             |
| AMT BIOS Features                                                |          | [Enabled] |      | → ←: Select Screen<br>↑ ↓: Select Item<br>Enter: Select<br>+/-: Change Opt.<br>F1: General Help<br>F2: Previous Values<br>F3: Optimized Defaults<br>F4: Save & Exit<br>ESC: Exit |             |
| Version 2.20.1275. Copyright (C) 2020, American Megatrends, Inc. |          |           |      |                                                                                                                                                                                  |             |

| Feature           | Option                | Description                                                                                                                                                                                                                            |
|-------------------|-----------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| AMT BIOS Features | [Disabled], [Enabled] | Select whether to enable or disable AMT BIOS Features.<br>When disabled AMT BIOS Features are no longer supported and user is no longer able to access MEBx Setup.<br>Note: This option does not disable Manageability Features in FW. |

Figure 51: BIOS Advanced Menu - Trusted Computing

| BIOS SETUP UTILITY                                               |          |            |      |                                                                                                                                                                                  |             |
|------------------------------------------------------------------|----------|------------|------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------|
| Main                                                             | Advanced | Power      | Boot | Security                                                                                                                                                                         | Save & Exit |
| Configuration                                                    |          |            |      |                                                                                                                                                                                  |             |
| Security Device Support                                          |          | [Disabled] |      |                                                                                                                                                                                  |             |
| No Security Device Found                                         |          |            |      | → ←: Select Screen<br>↑ ↓: Select Item<br>Enter: Select<br>+/-: Change Opt.<br>F1: General Help<br>F2: Previous Values<br>F3: Optimized Defaults<br>F4: Save & Exit<br>ESC: Exit |             |
| Version 2.20.1275. Copyright (C) 2020, American Megatrends, Inc. |          |            |      |                                                                                                                                                                                  |             |

| Feature                 | Option                | Description                                                                                                                                                              |
|-------------------------|-----------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Security Device Support | [Disabled], [Enabled] | Select whether to enable or disable BIOS support for security device.<br>O.S. will not show Security Device. TCG EFI protocol and INT1A interface will not be available. |

Figure 52: BIOS Advanced Menu - H/W Monitor

| BIOS SETUP UTILITY                                               |          |             |      |                        |             |
|------------------------------------------------------------------|----------|-------------|------|------------------------|-------------|
| Main                                                             | Advanced | Power       | Boot | Security               | Save & Exit |
| PC Health Status                                                 |          |             |      |                        |             |
| > Smart FAN Configuration                                        |          |             |      |                        |             |
| CPU Temperature                                                  |          | : +44 C     |      |                        |             |
| Memory Temperature                                               |          | : +30 C     |      |                        |             |
| System Temperature                                               |          | : +35 C     |      |                        |             |
| CPU Fan Speed                                                    |          | : 7042 RPM  |      | → ←: Select Screen     |             |
|                                                                  |          |             |      | ↑ ↓: Select Item       |             |
| +VCORE                                                           |          | : +0.752 V  |      | Enter: Select          |             |
| +VIN                                                             |          | : +12.000 V |      | +/-: Change Opt.       |             |
| +3VCC                                                            |          | : +3.328 V  |      | F1: General Help       |             |
| +3VSB                                                            |          | : +3.344 V  |      | F2: Previous Values    |             |
| +VBAT                                                            |          | : +3.168 V  |      | F3: Optimized Defaults |             |
| +5VA                                                             |          | : +5.088 V  |      | F4: Save & Exit        |             |
| +3VA                                                             |          | : +3.344 V  |      | ESC: Exit              |             |
| Version 2.20.1275. Copyright (C) 2020, American Megatrends, Inc. |          |             |      |                        |             |

Figure 53: BIOS Advanced Menu - H/W Monitor - Smart FAN Configuration

| BIOS SETUP UTILITY                                               |          |          |      |                        |             |
|------------------------------------------------------------------|----------|----------|------|------------------------|-------------|
| Main                                                             | Advanced | Power    | Boot | Security               | Save & Exit |
| Smart FAN Configuration                                          |          |          |      |                        |             |
| CPU FAN Setting                                                  |          | [Manual] |      |                        |             |
| Manual Duty*                                                     |          | 255      |      | → ←: Select Screen     |             |
| 1st Boundary Temperature**                                       |          | 30       |      | ↑ ↓: Select Item       |             |
| 1st FAN Speed**                                                  |          | 50       |      | Enter: Select          |             |
| 2nd Boundary Temperature**                                       |          | 40       |      | +/-: Change Opt.       |             |
| 2nd FAN Speed**                                                  |          | 100      |      | F1: General Help       |             |
| 3rd Boundary Temperature**                                       |          | 50       |      | F2: Previous Values    |             |
| 3rd FAN Speed**                                                  |          | 150      |      | F3: Optimized Defaults |             |
| 4th Boundary Temperature**                                       |          | 60       |      | F4: Save & Exit        |             |
| 4th FAN Speed**                                                  |          | 200      |      | ESC: Exit              |             |
| Version 2.20.1275. Copyright (C) 2020, American Megatrends, Inc. |          |          |      |                        |             |

\* This item appears only when selecting Manual for CPU FAN Setting.

\*\* These items appear only when selecting Smart for CPU FAN Setting.

| Feature | Option | Description |
|---------|--------|-------------|
|---------|--------|-------------|

| Feature         | Option            | Description                      |
|-----------------|-------------------|----------------------------------|
| CPU FAN Setting | [Manual], [Smart] | Switch the CPU FAN control mode. |

Figure 54: BIOS Advanced Menu - Network Stack

| BIOS SETUP UTILITY                                                                                                                                                               |          |            |      |          |             |
|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------|------------|------|----------|-------------|
| Main                                                                                                                                                                             | Advanced | Power      | Boot | Security | Save & Exit |
| Network Stack                                                                                                                                                                    |          | [Disabled] |      |          |             |
| Ipv4 PXE Support*                                                                                                                                                                |          | [Disabled] |      |          |             |
| Ipv4 HTTP Support*                                                                                                                                                               |          | [Disabled] |      |          |             |
| Ipv6 PXE Support*                                                                                                                                                                |          | [Disabled] |      |          |             |
| Ipv6 HTTP Support*                                                                                                                                                               |          | [Disabled] |      |          |             |
| IPSEC Certificate*                                                                                                                                                               |          | [Enabled]  |      |          |             |
| PXE boot wait time*                                                                                                                                                              |          | 0          |      |          |             |
| Media detect count*                                                                                                                                                              |          | 1          |      |          |             |
| → ←: Select Screen<br>↑ ↓: Select Item<br>Enter: Select<br>+/-: Change Opt.<br>F1: General Help<br>F2: Previous Values<br>F3: Optimized Defaults<br>F4: Save & Exit<br>ESC: Exit |          |            |      |          |             |
| Version 2.20.1275. Copyright (C) 2020, American Megatrends, Inc.                                                                                                                 |          |            |      |          |             |

\* These items appear only when enabling Network Stack.

| Feature           | Option                | Description                                                                                                            |
|-------------------|-----------------------|------------------------------------------------------------------------------------------------------------------------|
| Network Stack     | [Disabled], [Enabled] | Select whether to enable or disable UEFI network stack.                                                                |
| Ipv4 PXE Support  | [Disabled], [Enabled] | Select whether to enable or disable Ipv4 PXE boot support. If disabled, IPv4 PXE boot support will not be available.   |
| Ipv4 HTTP Support | [Disabled], [Enabled] | Select whether to enable or disable Ipv4 HTTP boot support. If disabled, IPv4 HTTP boot support will not be available. |
| Ipv6 PXE Support  | [Disabled], [Enabled] | Select whether to enable or disable Ipv6 PXE boot support. If disabled, IPv6 PXE boot support will not be available.   |
| Ipv6 HTTP Support | [Disabled], [Enabled] | Select whether to enable or disable Ipv6 HTTP boot support. If disabled, IPv6 HTTP boot support will not be available. |
| IPSEC Certificate | [Disabled], [Enabled] | Select whether to enable or disable IPSEC certificate for Ikev.                                                        |

### 8.2.3. Power Setup Menu

The Power setup menu provides functions and a sub-screen for power configurations. The following sub-screen function is included in the menu:

- ▶ WatchDog Timer Configuration

Figure 55: BIOS Power Setup Menu

| BIOS SETUP UTILITY                                               |          |                       |      |                        |             |
|------------------------------------------------------------------|----------|-----------------------|------|------------------------|-------------|
| Main                                                             | Advanced | Power                 | Boot | Security               | Save & Exit |
| Power Configuration                                              |          |                       |      |                        |             |
| ACPI Sleep State                                                 |          | [S3 (Suspend to RAM)] |      |                        |             |
| Restore AC Power Loss                                            |          | [Power Off]           |      | → ←: Select Screen     |             |
| Power Saving Mode                                                |          | [Disabled]            |      | ↑ ↓: Select Item       |             |
| Resume Event Control                                             |          |                       |      | Enter: Select          |             |
| Resume By LAN Device                                             |          | [Disabled]            |      | +/-: Change Opt.       |             |
| Resume By Ring Device                                            |          | [Disabled]            |      | F1: General Help       |             |
| Resume By RTC Alarm                                              |          | [Disabled]            |      | F2: Previous Values    |             |
| > WatchDog Timer Configuration                                   |          |                       |      | F3: Optimized Defaults |             |
|                                                                  |          |                       |      | F4: Save & Exit        |             |
|                                                                  |          |                       |      | ESC: Exit              |             |
| Version 2.20.1275. Copyright (C) 2020, American Megatrends, Inc. |          |                       |      |                        |             |

| Feature                | Option                                | Description                                                                                                                                                                                                                                                                                |
|------------------------|---------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| ACPI Sleep State       | [S3 (Suspend to RAM)]                 | Select whether to enable or disable suspend function and determine an appropriate suspend mode.                                                                                                                                                                                            |
| Restore AC Power Loss  | [Power Off], [Power On], [Last State] | This field controls whether the system will stay on after AC power is removed and then restored.<br>Select [Power Off] if you want the system to remain off after power restored.<br>Select [Power On] if you use a power strip to turn the system on.                                     |
| Power Saving Mode      | [Disabled], [EUP Enabled]             | Select whether to enable Power Saving Mode.<br>[EUP Enabled]: The system will enter to EUP Power Saving Mode during power off.<br>[DeepSx Enabled]: The system will enter to DeepSx Power Saving Mode during S4 / S5 power off.<br>[Disabled]: Disables function of all Power Saving Mode. |
| Resume By LAN 1 Device | [Disabled], [Enabled]                 | Select whether to enable or disable Wake from LAN Device.                                                                                                                                                                                                                                  |
| Resume By Ring Device  | [Disabled], [Enabled]                 | Select whether to enable or disable Wake from Ring Device.                                                                                                                                                                                                                                 |
| Resume By RTC Alarm    | [Disabled], [Enabled]                 | Select whether to enable or disable Wake Up on Alarm, to turn on your system on a special day of the month.                                                                                                                                                                                |

Figure 56: BIOS Power Setup Menu - WatchDog Timer Configuration

| BIOS SETUP UTILITY |
|--------------------|
|--------------------|

| Main                                                             | Advanced | Power      | Boot | Security               | Save & Exit |
|------------------------------------------------------------------|----------|------------|------|------------------------|-------------|
| WatchDog Timer Configuration                                     |          |            |      |                        |             |
| WDT Function                                                     |          | [Disabled] |      | → ←: Select Screen     |             |
| WDT Count Mode*                                                  |          | [Second]   |      | ↑ ↓: Select Item       |             |
| WDT Timer*                                                       |          | 30         |      | Enter: Select          |             |
|                                                                  |          |            |      | +/-: Change Opt.       |             |
|                                                                  |          |            |      | F1: General Help       |             |
|                                                                  |          |            |      | F2: Previous Values    |             |
|                                                                  |          |            |      | F3: Optimized Defaults |             |
|                                                                  |          |            |      | F4: Save & Exit        |             |
|                                                                  |          |            |      | ESC: Exit              |             |
| Version 2.20.1275. Copyright (C) 2020, American Megatrends, Inc. |          |            |      |                        |             |

\* These items appear only when enabling WDT Function.

| Feature        | Option                | Description                                                  |
|----------------|-----------------------|--------------------------------------------------------------|
| WDT Function   | [Disabled], [Enabled] | Select whether to enable or disable WatchDog Timer function. |
| WDT Count Mode | [Second], [Minute]    | Select WatchDog Count Mode: Second or Minute.                |

## 8.2.4. Boot Setup Menu

The boot setup menu lists the for boot device priority order, that is generated dynamically.

Figure 57: BIOS Boot Setup Menu

| BIOS SETUP UTILITY                                               |          |                            |      |                        |             |
|------------------------------------------------------------------|----------|----------------------------|------|------------------------|-------------|
| Main                                                             | Advanced | Power                      | Boot | Security               | Save & Exit |
| Boot Configuration                                               |          |                            |      |                        |             |
| Full Screen LOGO Display                                         |          | [Disabled]                 |      |                        |             |
| Setup Prompt Timeout                                             |          | 1                          |      | → ←: Select Screen     |             |
| Bootup NumLock State                                             |          | [On]                       |      | ↑ ↓: Select Item       |             |
| CSM Support                                                      |          | [Disabled]                 |      | Enter: Select          |             |
| Boot Option Filter                                               |          | [UEFI Only]                |      | +/-: Change Opt.       |             |
| Boot Option Priorities                                           |          |                            |      | F1: General Help       |             |
| Boot Option #1                                                   |          | [UEFI: Built-in EFI Shell] |      | F2: Previous Values    |             |
|                                                                  |          |                            |      | F3: Optimized Defaults |             |
|                                                                  |          |                            |      | F4: Save & Exit        |             |
|                                                                  |          |                            |      | ESC: Exit              |             |
| Version 2.20.1275. Copyright (C) 2020, American Megatrends, Inc. |          |                            |      |                        |             |

| Feature                  | Option                                 | Description                                                                                                                                                                                              |
|--------------------------|----------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Full Screen LOGO Display | [Disabled], [Enabled]                  | Select whether to enable or disable to display logo screen.                                                                                                                                              |
| Bootup NumLock State     | [On], [Off]                            | This field indicates the state of the NumLock feature of the keyboard after Startup.<br>[On]: The keys on the keypad will act as numeric keys.<br>[Off]: The keys on the keypad will act as cursor keys. |
| CSM Support              | [Enabled], [Disabled]                  | Select whether to enable or disable CSM support.                                                                                                                                                         |
| Boot Option Filter       | [UEFI only]                            | This option controls Legacy / UEFI ROMs priority.                                                                                                                                                        |
| Boot Option #1           | [UEFI: Built-in EFI Shell], [Disabled] | Select an option for first boot device.                                                                                                                                                                  |

## 8.2.5. Security Setup Menu

The Security setup menu provides information about the passwords and functions for specifying the security settings. The passwords are case-sensitive. The 3.5"-SBC-WLU provides no factory-set passwords.

### NOTICE

If there is already a password installed, the system asks for this first. To clear a password, simply enter nothing and acknowledge by pressing <RETURN>. To set a password, enter it twice and acknowledge by pressing <RETURN>.

Figure 58: BIOS Security Setup Menu

| BIOS SETUP UTILITY                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |          |       |      |                        |             |
|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------|-------|------|------------------------|-------------|
| Main                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                | Advanced | Power | Boot | Security               | Save & Exit |
| Password Description<br><br>If ONLY the Administrator's password is set, then this only limits access to Setup and is only asked for when entering Setup<br><br>If ONLY the User's password is set, then this is a power on password and must be entered to boot or enter Setup. In Setup the User will have Administrator rights<br><br>The password length must be in the following range:<br><br>Minimum Length3<br><br>Maximum length20<br><br>Administrator Password<br><br>User Password<br><br>> Secure Boot |          |       |      |                        |             |
|                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |          |       |      | → ←: Select Screen     |             |
|                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |          |       |      | ↑ ↓: Select Item       |             |
|                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |          |       |      | Enter: Select          |             |
|                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |          |       |      | +/-: Change Opt.       |             |
|                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |          |       |      | F1: General Help       |             |
|                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |          |       |      | F2: Previous Values    |             |
|                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |          |       |      | F3: Optimized Defaults |             |
|                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |          |       |      | F4: Save & Exit        |             |
| ESC: Exit                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           |          |       |      |                        |             |
| Version 2.20.1275. Copyright (C) 2020, American Megatrends, Inc.                                                                                                                                                                                                                                                                                                                                                                                                                                                    |          |       |      |                        |             |

| Feature                | Description                |
|------------------------|----------------------------|
| Administrator Password | Set administrator password |
| User Password          | Set user password          |



If only the administrator's password is set, then only access to setup is limited. The password is only entered when entering setup.

If only the user's password is set, then the password is a power on password and must be entered to boot or enter setup. Within the setup menu the user has administrator rights.

Password length requirements are maximum 20 characters and minimum 3 characters.

### 8.2.5.1. Remember the password

It is highly recommended to keep a record of all passwords in a safe place. Forgotten passwords results in being locked out of the system.

If the system cannot be booted because the User Password or the Supervisor Password are not know, contact Kontron Support for further assistance.



---

**HDD security passwords cannot be cleared using the above method.**

---

## 8.2.6. Save & Exit Setup Menu

The exit setup menu provides functions for handling changes made to the UEFI BIOS settings and the exiting of the setup program.

Figure 59: BIOS Save & Exit Setup Menu

| BIOS SETUP UTILITY                                                                                                                 |          |       |      |                        |             |
|------------------------------------------------------------------------------------------------------------------------------------|----------|-------|------|------------------------|-------------|
| Main                                                                                                                               | Advanced | Power | Boot | Security               | Save & Exit |
| Save Changes and Reset<br>Discard Changes and Reset<br><br>Save Options<br>Save Changes<br>Discard Changes<br><br>Restore Defaults |          |       |      |                        |             |
|                                                                                                                                    |          |       |      | → ←: Select Screen     |             |
|                                                                                                                                    |          |       |      | ↑ ↓: Select Item       |             |
|                                                                                                                                    |          |       |      | Enter: Select          |             |
|                                                                                                                                    |          |       |      | +/-: Change Opt.       |             |
|                                                                                                                                    |          |       |      | F1: General Help       |             |
|                                                                                                                                    |          |       |      | F2: Previous Values    |             |
|                                                                                                                                    |          |       |      | F3: Optimized Defaults |             |
|                                                                                                                                    |          |       |      | F4: Save & Exit        |             |
|                                                                                                                                    |          |       |      | ESC: Exit              |             |
| Version 2.20.1275. Copyright (C) 2020, American Megatrends, Inc.                                                                   |          |       |      |                        |             |

| Feature                  | Description                                                                                                                                                                                                                                                                                                                                                                                         |
|--------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Save Changes and Exit    | Exit system setup after saving the changes. Once you are finished making your selections, choose this option from the Exit menu to ensure the values you selected are saved to the CMOS RAM. The CMOS RAM is sustained by an onboard backup battery and stays on even when the PC is turned off. When you select this option, a confirmation window appears. Select [Yes] to save changes and exit. |
| Discard Changes and Exit | Exit system setup without saving any changes. Select this option only if you do not want to save the changes that you made to the Setup program. If you made changes to fields other than system date, system time, and password, the BIOS asks for a confirmation before exiting.                                                                                                                  |
| Save Changes             | Save changes done so far to any of the setup values. This option allows you to save the selections you made. After selecting this option, a confirmation appears. Select [Yes] to save any changes.                                                                                                                                                                                                 |
| Discard Changes          | Discards changes done so far to any of the setup values. This option allows you to discard the selections you made and restore the previously saved values. After selecting this option, a confirmation appears. Select [Yes] to discard any changes and load the previously saved values.                                                                                                          |
| Restore Defaults         | Restore Default values for all the setup values. This option allows you to load optimal default values for each of the parameters on the Setup menus, which will provide the best performance settings for your system. The F9 key can be used for this operation.                                                                                                                                  |

## Appendix A: List of Acronyms



The following table does not contain the complete acronyms used in signal names, signal type definitions or similar. A description of the signals is included in the I/O Connector and Internal connector chapters within this user guide.

Table 48: List of Acronyms

|        |                                                |
|--------|------------------------------------------------|
| 2D     | Two-Dimensional                                |
| 3D     | Three-Dimensional                              |
| AT     | Advanced Technology                            |
| ATX    | Advanced Technology eXtended                   |
| BGA    | Ball Grid Array                                |
| BIOS   | Basic Input / Output System                    |
| BSP    | Board Support Package                          |
| CMOS   | Complementary Metal Oxide Semiconductor        |
| CPU    | Central Processing Unit                        |
| DC     | Direct Current                                 |
| DDC    | Display Data Channel                           |
| DIO    | Digital Input / Output                         |
| DP     | DisplayPort                                    |
| ECC    | Error-Correcting Code                          |
| EEE    | Electrical and Electronic Equipment            |
| EOS    | Electrical OverStress                          |
| ESD    | ElectroStatic Discharge                        |
| GbE    | Gigabit Ethernet                               |
| HDD    | Hard Disk Drive                                |
| HDMI   | High Definition Multimedia Interface           |
| LAN    | Local Area Network                             |
| LED    | Light Emitting Device                          |
| LVDS   | Low-Voltage Differential Signaling             |
| ME F/W | Management Engine Firmware                     |
| mPCIe  | mini Peripheral Component Interconnect express |
| NGFF   | Next Generation Form Factor                    |
| PC-AT  | Personal Computer - Advanced Technology        |
| PCB    | Printed Circuit Board                          |
| PSU    | Power Supply Unit                              |
| PVC    | PolyViny Chloride                              |
| PWM    | Pulse Width Modulation                         |
| RAM    | Random Access Memory                           |
| ROM    | Read-Only Memory                               |

|         |                                           |
|---------|-------------------------------------------|
| RTC     | Real-Time Clock                           |
| SATA    | Serial Advanced Technology Attachment     |
| SD      | Secure Digital memory card                |
| SDP     | Serial Download Protocol                  |
| SELV    | Safety Extra-Low Voltage                  |
| SIM     | Subscriber Identity Module                |
| SMBus   | System Management Bus                     |
| SoC     | System on Chip                            |
| SO-DIMM | Small Outline Dual In-line Memory Module  |
| SPD     | Serial Presence Detect                    |
| SPI     | Serial Peripheral Interface               |
| TDP     | Thermal Design Power                      |
| TPM     | Trusted Platform Module                   |
| UEFI    | Unified Extensible Firmware Interface     |
| USB     | Universal Serial Bus                      |
| UTP     | Update Transfer Protocol                  |
| VGA     | Video Graphics Array                      |
| WDT     | WatchDog Timer                            |
| WEEE    | Waste Electrical and Electronic Equipment |
|         |                                           |
|         |                                           |
|         |                                           |
|         |                                           |
|         |                                           |



## About Kontron

Kontron is a global leader in IoT / Embedded Computing Technology (ECT) and offers individual solutions in the areas of Internet of Things (IoT) and Industry 4.0 through a combined portfolio of hardware, software and services. With its standard and customized products based on highly reliable state-of-the-art technologies, Kontron provides secure and innovative applications for a wide variety of industries. As a result, customers benefit from accelerated time-to-market, lower total cost of ownership, extended product lifecycles and the best fully integrated applications.

For more information, please visit: [www.kontron.com](http://www.kontron.com)



## Global Headquarters

### Kontron Europe GmbH

Gutenbergstraße 2  
85737 Ismaning  
Germany  
Tel.: +49 821 4086-0  
Fax: +49 821 4086-111  
[info@kontron.com](mailto:info@kontron.com)